

LD350 LD355



- Multifunction touch-screen display for incremental encoders
- Speed and position indicator, frequency counter, process meter, timer, stopwatch, ...
- Input frequencies up to 1MHz
- Digital, analogue, serial and relay outputs
- DC / AC power supply: 18÷30Vdc or 115÷230Vac

Suitable for the following models:

- LD350/LD355 touch-screen display
- LD350/LD355-PM touch-screen display with 115/230Vac power supply
- LD350/LD355-DO touch-screen display with four control outputs + RS-232 serial interface
- LD350/LD355-AVI touch-screen display with analogue output + four control outputs + RS-232 serial interface
- LD350/LD355-RO touch-screen display with two relay outputs

General Contents

Preliminary information	10
1 - Safety summary	12
2 - Identification	14
3 - Mounting instructions	15
4 - Electrical connections	17
5 - Display and touch screen	26
6 - Menus and parameters	28
7 - Appendix	74
8 - Parameters / serial codes	75

This publication was produced by Lika Electronic s.r.l. 2018. All rights reserved. Tutti i diritti riservati. Alle Rechte vorbehalten. Todos los derechos reservados. Tous droits réservés.

This document and information contained herein are the property of Lika Electronic s.r.l. and shall not be reproduced in whole or in part without prior written approval of Lika Electronic s.r.l. Translation, reproduction and total or partial modification (photostat copies, film and microfilm included and any other means) are forbidden without written authorisation of Lika Electronic s.r.l.

The information herein is subject to change without notice and should not be construed as a commitment by Lika Electronic s.r.l. Lika Electronic s.r.l. reserves the right to make all modifications at any moments and without forewarning.

This manual is periodically reviewed and revised. As required we suggest checking if a new or updated edition of this document is available at Lika Electronic s.r.l.'s website. Lika Electronic s.r.l. assumes no responsibility for any errors or omissions in this document. Critical evaluation of this manual by the user is welcomed. Your comments assist us in preparation of future documentation, in order to make it as clear and complete as possible. Please send an e-mail to the following address info@lika.it for submitting your comments, suggestions and criticisms.

The logo for Lika Electronic s.r.l. features the word "lika" in a bold, lowercase, sans-serif typeface. The letters are black and have a modern, clean appearance.

General contents

General contents.....	3
Subject index.....	7
Typographic and iconographic conventions.....	9
Preliminary information.....	10
Operational modes.....	10
Functional diagram.....	11
1 - Safety summary.....	12
1.1 Safety.....	12
1.2 Electrical safety.....	12
1.3 Mechanical safety.....	12
2 - Identification.....	14
3 - Mounting instructions.....	15
3.1 Overall dimensions.....	15
3.2 Installation.....	16
3.3 Cleaning, maintenance and service notes.....	16
4 - Electrical connections.....	17
4.1 DC power supply.....	17
4.2 AC power supply (PM order code).....	18
4.3 Auxiliary voltage output.....	18
4.4 A, B incremental inputs (LD350 model).....	19
4.4.1 Wiring of the incremental inputs.....	19
4.4.2 Note about mechanical switching contacts.....	19
4.5 A, /A, B, /B incremental inputs (LD355 model).....	20
4.5.1 Wiring of the incremental inputs.....	20
4.6 Control inputs.....	21
4.6.1 Wiring of the control inputs.....	21
4.6.2 Note about mechanical switching contacts.....	21
4.7 Analogue output (AVI order code).....	22
4.8 Serial interface (AVI and DO order codes).....	23
4.9 Control outputs (AVI and DO order codes).....	24
4.9.1 Wiring of the control outputs.....	24
4.10 Relay outputs (RO order code).....	25
4.10.1 Wiring of the relay outputs.....	25
5 - Display and touch screen.....	26
5.1 Screen structure for parametrization.....	26
5.2 Screen structure during operation.....	27
6 - Menus and parameters.....	28
6.1 Overview of the structure.....	28
6.2 General menu.....	33
Operational mode.....	33
Encoder properties LD350.....	33
Encoder properties LD355.....	33
Encoder supply.....	34
Counting direction.....	34
Scale units.....	34
Linearization mode.....	35

Pin preselection.....	36
Pin parameter.....	36
Back up memory.....	36
Factory settings.....	36
6.3 Speed operation mode menu.....	37
Display value.....	37
Base frequency (Hz).....	37
Decimal point.....	37
Sampling time (s).....	38
Wait time (s).....	38
Standstill time (s).....	39
Average filter.....	39
For/Rev detection.....	39
6.4 Process Time operation mode menu.....	40
Display format.....	40
Display value.....	40
Base frequency (Hz).....	40
Sampling time (s).....	41
Wait time (s).....	41
Standstill time (s).....	42
Average filter.....	42
6.5 Timer operation mode menu.....	43
Time base.....	43
Start / Stop.....	43
Auto set / reset.....	43
Latch function.....	44
Set value.....	44
Inc / Dec mode.....	44
6.6 Counter operation mode menu.....	45
Count mode.....	45
Factor.....	45
Set value.....	46
Decimal point.....	46
Batch mode.....	46
Batch set value.....	47
6.7 Velocity operation mode menu.....	48
Start / Stop.....	48
Display value.....	48
Base time (s).....	48
Decimal point.....	48
Wait time (s).....	49
Standstill time (s).....	49
6.8 Preselection values menu.....	50
Preselection 1.....	50
Preselection 2.....	50
Preselection 3.....	50
Preselection 4.....	50
6.9 Preselection 1 menu.....	51
Mode 1.....	51

Hysteresis 1	53
Pulse time 1 (s)	53
Output target 1	53
Output polarity 1	53
Output lock 1	54
Start up delay 1 (s)	54
Event color 1	54
6.10 Preselection 2 menu	55
Mode 2	55
Hysteresis 2	55
Pulse time 2 (s)	55
Output target 2	55
Output polarity 2	55
Output lock 2	55
Start up delay 2 (s)	56
Event color 2	56
6.11 Preselection 3 menu	57
Mode 3	57
Hysteresis 3	57
Pulse time 3 (s)	57
Output target 3	57
Output polarity 3	57
Output lock 3	57
Start up delay 3 (s)	58
Event color 3	58
6.12 Preselection 4 menu	59
Mode 4	59
Hysteresis 4	59
Pulse time 4 (s)	59
Output target 4	59
Output polarity 4	59
Output lock 4	60
Start up delay 4 (s)	60
Event color 4	60
6.13 Serial menu	61
Unit number	61
Serial baud rate	61
Serial format	61
Serial init	62
Serial protocol	62
Serial timer (s)	63
Serial value	63
6.14 Analog menu	64
Analog format	64
Analog start	64
Analog end	64
Analog gain (%)	65
Analog offset	65
6.15 Command menu	66

Input 1 action.....	66
Input 1 config.....	68
Input 2 action.....	68
Input 2 config.....	68
Input 3 action.....	68
Input 3 config.....	68
6.16 Display menu.....	69
Color.....	69
Brightness (%).....	69
Contrast.....	69
Screen saver (s).....	69
Up-date time (s).....	70
Font.....	70
6.17 Linearization menu.....	71
P1(X).....	71
P24(X).....	71
P1(Y).....	71
P24(Y).....	71
6.17.1 Description of the linearisation function.....	71
7 - Appendix.....	74
7.1 Data readout via serial interface.....	74
8 - Parameters / serial codes.....	75
8.1 General menu.....	75
8.2 Speed operation mode menu.....	75
8.3 Process Time operation mode menu.....	76
8.4 Timer operation mode menu.....	76
8.5 Counter operation mode menu.....	76
8.6 Velocity operation mode menu.....	77
8.7 Preselection values menu.....	77
8.8 Preselection 1 menu.....	77
8.9 Preselection 2 menu.....	78
8.10 Preselection 3 menu.....	78
8.11 Preselection 4 menu.....	78
8.12 Serial menu.....	79
8.13 Analog menu.....	79
8.14 Command menu.....	79
8.15 Display menu.....	80
8.16 Linearization menu.....	80
8.17 Serial codes of commands.....	82

Subject index

A

Analog end.....	64
Analog format.....	64
Analog gain (%).....	65
Analog offset.....	65
Analog start.....	64
Auto set / reset.....	43
Average filter.....	39, 42

B

Back up memory.....	36
Base frequency (Hz).....	37, 40
Base time (s).....	48
Batch mode.....	46
Batch set value.....	47
Brightness (%).....	69

C

Color.....	69
Contrast.....	69
Count mode.....	45
Counting direction.....	34

D

Decimal point.....	37, 46, 48
Display format.....	40
Display value.....	37, 40, 48

E

Encoder properties LD350.....	33
Encoder properties LD355.....	33
Encoder supply.....	34
Event color 1.....	54
Event color 2.....	56
Event color 3.....	58
Event color 4.....	60

F

Factor.....	45
Factory settings.....	36
Font.....	70
For/Rev detection.....	39

H

Hysteresis 1.....	53
Hysteresis 2.....	55
Hysteresis 3.....	57
Hysteresis 4.....	59

I

Inc / Dec mode.....	44
Input 1 action.....	66
Input 1 config.....	68

Input 2 action.....	68
Input 2 config.....	68
Input 3 action.....	68
Input 3 config.....	68

L

Latch function.....	44
Linearization mode.....	35

M

Mode 1.....	51
Mode 2.....	55
Mode 3.....	57
Mode 4.....	59

O

Operational mode.....	33
Output lock 1.....	54
Output lock 2.....	55
Output lock 3.....	57
Output lock 4.....	60
Output polarity 1.....	53
Output polarity 2.....	55
Output polarity 3.....	57
Output polarity 4.....	59
Output target 1.....	53
Output target 2.....	55
Output target 3.....	57
Output target 4.....	59

P

P1(X).....	71
P1(Y).....	71
P24(X).....	71
P24(Y).....	71
Pin parameter.....	36
Pin preselection.....	36
Preselection 1.....	50
Preselection 2.....	50
Preselection 3.....	50
Preselection 4.....	50
Pulse time 1 (s).....	53
Pulse time 2 (s).....	55
Pulse time 3 (s).....	57
Pulse time 4 (s).....	59

S

Sampling time (s).....	38, 41
Scale units.....	34
Screen saver (s).....	69
Serial baud rate.....	61

Serial format.....	61
Serial init.....	62
Serial protocol.....	62
Serial timer (s).....	63
Serial value.....	63
Set value.....	44, 46
Standstill time (s).....	39, 42, 49
Start / Stop.....	43, 48
Start up delay 1 (s).....	54
Start up delay 2 (s).....	56

Start up delay 3 (s).....	58
Start up delay 4 (s).....	60
T	
Time base.....	43
U	
Unit number.....	61
Up-date time (s).....	70
W	
Wait time (s).....	38, 41, 49

Typographic and iconographic conventions

In this guide, to make it easier to understand and read the text the following typographic and iconographic conventions are used:

- parameters and objects both of the device and the interface are coloured in **GREEN**;
- alarms are coloured in **RED**;
- states are coloured in **FUCSIA**.

When scrolling through the text some icons can be found on the side of the page: they are expressly designed to highlight the parts of the text which are of great interest and significance for the user. Sometimes they are used to warn against dangers or potential sources of danger arising from the use of the device. You are advised to follow strictly the instructions given in this guide in order to guarantee the safety of the user and ensure the performance of the device. In this guide the following symbols are used:

	This icon, followed by the word WARNING, is meant to highlight the parts of the text where information of great significance for the user can be found: user must pay the greatest attention to them! Instructions must be followed strictly in order to guarantee the safety of the user and a correct use of the device. Failure to heed a warning or comply with instructions could lead to personal injury and/or damage to the unit or other equipment.
	This icon, followed by the word NOTE, is meant to highlight the parts of the text where important notes needful for a correct and reliable use of the device can be found. User must pay attention to them! Failure to comply with instructions could cause the equipment to be set wrongly: hence a faulty and improper working of the device could be the consequence.
	This icon is meant to highlight the parts of the text where suggestions useful for making it easier to set the device and optimize performance and reliability can be found. Sometimes this symbol is followed by the word EXAMPLE when instructions for setting parameters are accompanied by examples to clarify the explanation.

Preliminary information

This guide is designed to provide the most complete information the operator needs to correctly and safely install and operate the **LD350 and LD355 touch-screen indicator** series.

LD350 and LD355 touch-screen indicators are designed to interface HTL/TTL encoders or NPN/PNP/NAMUR sensors and offer several operating modes such as position indicator, tachometer and speed indicator, frequency / RPM indicator, process meter, counter, timer, stopwatch, etc. The input frequency can be up to 1 MHz. They also implement the counting direction and the linearisation functions.

They feature a touch screen and 7-segment graphic display with a complete set of plain text, symbols and units. The LED display is bright and provides high contrast readability and also allows the background light to turn red, green or yellow in the event of the set occurrences such as when the threshold limits are exceeded. The combination of plain text and touch screen functions make the parametrization very user-friendly and intuitive.

LD350 touch-screen indicator provides two incremental AB inputs for PNP/NPN/NAMUR/TRI-STATE type signals.

LD355 touch-screen indicator provides four incremental AB /AB inputs for HTL/RS-422 type signals.

In the series the following models are available:

- **LD350 / LD355** touch-screen indicator standard version;
- **LD350- / LD355-PM** provides additional 115-230Vac power supply;
- **LD350- / LD355-AVI** provides additional 16-bit analogue output, four control outputs and RS-232 serial interface;
- **LD350- / LD355-DO** further offers four control outputs and RS-232 serial interface;
- **LD350- / LD355-RO** is equipped with two relay outputs.

All options (-PM, -AVI, -DO, -RO) can be freely combined.

For technical specifications please refer to the product datasheet.

To make it easier to read the text, this guide can be divided into two main sections.

In the first section (from section 1 to section 4) general information concerning the safety, the mechanical installation and the electrical connection.

In the second section (from section 5 to section 8) both general and specific information is given on the operator menu and the setup procedure.

Operational modes


All functions can be configured in the parameter menu.

The device can be set to one of the following operation modes:

- **SPEED** (only input A or input B are used, depending on the parameter setting), see the "6.3 Speed operation mode menu" section on page 37.
 - Tachometer / speed indicator

- Measurement of frequency / RMP indicator
 - Monitoring functions for speed and standstill
- PROCESS TIME (only input A is used), see the "6.4 Process Time operation mode menu" section on page 40.
 - Processing time indicator (reciprocal speed)
 - Baking time indicator
 - Flow time indicator
- TIMER (only input A or input B are used, depending on the parameter setting), see the "6.5 Timer operation mode menu" section on page 43
 - Operation as stopwatch (start / stop function can be freely parametrized)
 - Counter for working hours
 - Period measurement
- COUNTER (input A and input B are both used), see the "6.6 Counter operation mode menu" section on page 45
 - Pulse counter / sum or differential counter
 - Up or down counter
 - Position indicator
 - Quadrature counter
 - Batch counter
- VELOCITY (input A operates as a start input and input B operates as a stop input), see the "6.7 Velocity operation mode menu" section on page 48
 - Runtime measurement as speed indicator

Functional diagram



1 – Safety summary



1.1 Safety

- Always adhere to the professional safety and accident prevention regulations applicable to your country during device installation and operation;
- installation and maintenance operations have to be carried out by qualified personnel only, with power supply disconnected and stationary mechanical parts;
- device must be used only for the purpose appropriate to its design: use for purposes other than those for which it has been designed could result in serious personal and/or the environment damage;
- high current, voltage and moving mechanical parts can cause serious or fatal injury;
- warning ! Do not use in explosive or flammable areas;
- failure to comply with these precautions or with specific warnings elsewhere in this manual violates safety standards of design, manufacture, and intended use of the equipment;
- Lika Electronic assumes no liability for the customer's failure to comply with these requirements.



1.2 Electrical safety

- Turn OFF power supply before connecting the device;
- connect following to explanation in the "4 - Electrical connections" section on page 17;
- in compliance with 2014/30/EU norm on electromagnetic compatibility, following precautions must be taken:
 - before handling and installing the equipment, discharge electrical charge from your body and tools which may come in touch with the device;
 - power supply must be stabilized without noise; install EMC filters on device power supply if needed;
 - always use shielded cables (twisted pair cables whenever possible);
 - avoid cables runs longer than necessary;
 - avoid running the signal cable near high voltage power cables;
 - mount the device as far as possible from any capacitive or inductive noise source; shield the device from noise source if needed;
 - minimize noise by connecting the unit to ground (GND). Make sure that ground (GND) is not affected by noise. The connection point to ground can be situated both on the device side and on user's side. The best solution to minimize the interference must be carried out by the user.



1.3 Mechanical safety

- Install the device following strictly the information in the "3 - Mounting instructions" section;
- do not disassemble the unit;
- do not tool the unit;

- delicate electronic equipment: handle with care;
- do not subject the device to knocks or shocks;
- respect the environmental characteristics of the device.

2 - Identification

Device can be identified through the **order code** and the **serial number** printed on the label applied to its body. Information is listed in the delivery document too. Please always quote the order code and the serial number when reaching Lika Electronic for purchasing spare parts or needing assistance. For any information on the technical characteristics of the product, refer to the technical catalogue.



Warning: devices having order code ending with "/Sxxx" may have mechanical and electrical characteristics different from standard and be supplied with additional documentation for special connections (Technical info).

3 - Mounting instructions




WARNING

Installation and maintenance operations have to be carried out by qualified personnel only, with power supply disconnected and mechanical parts compulsorily in stop.

3.1 Overall dimensions

Mount the display into the provided cut-out (w x h approx. 91 x 43 mm, 3.58" x 1.69") without panel clips.

Install panel clips on the display housing and screw until the unit is fixed.



Panel cut out: 91 x 43 mm (3.58" x 1.69")

3.2 Installation

The device is allowed to be installed and operated only within the permissible temperature range (-20°C +60°C / -4°F +140°F). Please ensure an adequate ventilation and avoid any direct contact between the device and gases / liquids. Before installation or maintenance, the unit must be disconnected from all voltage sources. Furthermore it must be ensured that no danger can arise in the event of contact with the disconnected voltage sources.

Devices which are supplied by AC voltages must be connected only by means of switches or circuit breakers with low voltage circuit. The switch or circuit breaker must be installed as near as possible to the device and further indicated as separator.

Incoming as well as outgoing wires and wires for extra low voltages (ELV) must be separated from dangerous electrical cables (SELV circuits) by using double or increased insulation.

All selected wires and insulations must comply with the provided voltage and temperature ranges. Furthermore all country and application specific standards which are relevant for structure, form and quality of the wires must be ensured. Indications about the permissible wire cross sections for wiring are described in the product datasheet.

Before starting the unit for the first time it must be ensured that all connections and wires are firmly plugged in and secured to the screw terminal blocks. All terminal blocks (including unused ones) must be fastened by turning the relevant screws clockwise up to the end position.

Overvoltages at the connections must be limited to values in accordance with the overvoltage category II.

For placement, wiring, environmental conditions as well as shielding and earthing/grounding of the supply lines you must comply with the general standards stated for industrial automation industry and the specific shielding instructions provided by the manufacturer.

3.3 Cleaning, maintenance and service notes

To clean the unit please just use a slightly damp (not wet!), soft cloth. For the rear side no cleaning is necessary. For an unscheduled, individual cleaning of the rear side the maintenance technicians or installation operators are self-responsible.

During normal operation no maintenance is necessary. In case of unexpected problems, failures or malfunctions the device must be shipped back to the manufacturer for any checking, adjustment or repair (if necessary). Unauthorized opening and repair operations can have negative effects or cause failures to the protection measures of the unit.


4 – Electrical connections



WARNING

Power supply must be turned off before performing any electrical connection!

The terminal block screws must be tightened using a slotted screwdriver having a 2 mm wide blade.



4.1 DC power supply

DC power supply technical specifications

Input voltage:	18Vdc ... 30Vdc
Protection circuit:	reverse polarity protection
Power consumption:	approx. 100 mA (unloaded)
Fuse protection:	external fuse T 0.5 A

The unit accepts DC supply from 18 to 30 V through terminal blocks 1 and 2. The power consumption depends on the level of the supply voltage (approx. 100 mA) and the additional current required by the Auxiliary Voltage output (3 – GND + 4 – Aux. Out, see the "4.3 Auxiliary voltage output" section on page 18).

All GND terminal blocks are internally connected.



NOTE

For AC power supply (PM order code) see the following section.

4.2 AC power supply (PM order code)

AC power supply technical specifications

Input voltage:	115Vac ... 230Vac (50÷60Hz)
Power consumption:	approx. 3 VA (unloaded)
Fuse protection:	external fuse T 0.1 A

The unit with PM order code also accepts AC power supply from 115 V to 230 V through terminal blocks 24 and 25. The power consumption depends on the level of the supply voltage (approx. 3 VA) and the additional current required by the Auxiliary Voltage output (3 – GND + 4 – Aux. Out, see the "4.3 Auxiliary voltage output" section below).

Devices with PM order code can also be supplied with a DC voltage between 18 V and 30 V through terminals 1 and 2, see the previous "4.1 DC power supply" section.

4.3 Auxiliary voltage output

Auxiliary voltage output technical specifications (LD350 model)

DC version:	24Vdc (approx. 1 V lower than the power supply voltage), max. 250 mA
AC version:	24Vdc ($\pm 15\%$), max. 150 mA up to 45°C / 80 mA when more than 45°C

Auxiliary voltage output technical specifications (LD355 model)

DC version:	24Vdc (approx. 1 V lower than the power supply voltage), max. 250 mA or 5Vdc ($\pm 15\%$), max. 250 mA
AC version:	24Vdc ($\pm 15\%$) (max. 150 mA up to 45°C / 80 mA when more than 45°C) or 5Vdc ($\pm 15\%$), max. 250 mA

Terminal blocks 3 and 4 provide an auxiliary output useful for supplying sensors and encoders.

The output voltage level depends on the power supply.

DC version	AC version
The encoder voltage is approx. 1 V lower than the power supply voltage at terminal blocks 1 and 2 and should be loaded with max. 250 mA.	The encoder voltage is 24 Vdc ($\pm 15\%$) and should be loaded with max. 150 mA up to 45° Celsius. At higher temperature the maximum output current is reduced to 80 mA.

LD355 model allows the auxiliary voltage output to be set to either 24 Vdc or 5 Vdc. Refer to the **Encoder supply** parameter in the "6.2 General menu" section on page 33.

4.4 A, B incremental inputs (LD350 model)


A, B incremental inputs technical specifications

Number of inputs (channels):	2 (A, B)
Configuration:	PNP, NPN, Namur, Tri-State
Format:	HTL (Low = 0 ... 3 V, High = 9 ... 30 V)
Frequency:	max. 250 kHz
Load:	max. 6 mA / $R_i > 5 \text{ k}\Omega$ / 470 pF


The unit provides two inputs for HTL signals through terminal blocks 5 and 7. The characteristics of the incremental inputs (PNP, NPN, Namur or Tri-State) can be set in the **General** menu, see the **Encoder properties LD350** parameter in the "6.2 General menu" section on page 33.

4.4.1 Wiring of the incremental inputs


PNP




NPN



Namur



Tri-State



Unconnected PNP inputs are always "LOW" and unconnected NPN inputs are always "HIGH".

All inputs are designed to receive impulses from electrical impulse sources.



4.4.2 Note about mechanical switching contacts

When, exceptionally, mechanical contacts are used, please connect an external capacitor between GND (-) and the corresponding input (+). A capacity of 10 μF will reduce the input frequency to 20 Hz and miscounting due to contact bouncing will be eliminated.

4.5 A, /A, B, /B incremental inputs (LD355 model)


AB, /AB incremental inputs technical specifications

Number of inputs (channels):	4 (A, /A, B, /B)
Configuration:	RS-422, HTL differential, HTL PNP, HTL NPN
HTL differential:	HTL (Low = 0 ... 3 V, High = 9 ... 30 V)
HTL PNP / NPN:	max. 250 kHz
Load:	max. 3 mA / $R_i > 10 \text{ k}\Omega$ / 47 pF


The unit provides four pulse inputs at terminal blocks 5, 6, 7 and 8 for HTL/RS-422 signals. The characteristics of the incremental inputs can be set in the **General** menu, see the [Encoder properties LD355](#) parameter in the "6.2 General menu" section on page 33.

4.5.1 Wiring of the incremental inputs


RS-422




HTL differential



HTL PNP, single ended



HTL NPN, single ended



Unconnected PNP inputs are always "LOW" and unconnected NPN inputs are always "HIGH".

All inputs are designed to receive impulses from electrical impulse sources.

4.6 Control inputs


Control inputs technical specifications

Number of inputs:	3
Format:	HTL, PNP (Low = 0 ... 3 V, High = 9 ... 30 V)
Frequency:	max. 10 kHz
Load:	max. 2 mA / $R_i > 15 \text{ k}\Omega$ / 470 pF

The three control inputs at terminal blocks 10, 11 and 12 have HTL PNP characteristics.

In the **Command** menu (see the "6.15 Command menu" section on page 66) the operation of the control inputs can be set. Available functions are: reset the display value, display switching, locking the touch screen or release the lock function of the control or relay outputs.

4.6.1 Wiring of the control inputs



Unconnected control inputs are always "LOW".

All inputs are designed to receive impulses from an electronic impulse source.



4.6.2 Note about mechanical switching contacts

When, exceptionally, mechanical contacts are used, please connect an external capacitor between GND (-) and the corresponding input (+). A capacity of 10 μF will reduce the input frequency to 20 Hz and miscounting due to contact bouncing will be eliminated.

4.7 Analogue output (AVI order code)

Analogue output technical specifications

Configuration:	Current or voltage operation
Voltage output (0):	-10 V ... +10 V (max. 2 mA)
Current output (1):	0 ... 20 mA (burden: max. 270 Ohm)
Current output (2):	4 ... 20 mA (burden: max. 270 Ohm)
Resolution:	16 bits
Accuracy:	±0.1%
Reaction time:	< 150 ms

A 16 bit analogue output is available through terminal blocks 13 and 14 / 15. It can be configured and scaled in the **Analog** menu, see the "6.14 Analog menu" section on page 64.

The following configurations are available (see the **Analog format** parameter on page 64):

- 0** Voltage output: -10 V ... +10 V
- 1** Current output: 0 ... 20 mA
- 2** Current output: 4 ... 20 mA

The analogue output is proportional to the display value and is referenced to potential AGND. AGND and GND are internally connected.



WARNING

Voltage and current outputs of the analogue output cannot be operated simultaneously.

4.8 Serial interface (AVI and DO order codes)

Serial interface technical specifications


Format:	RS-232
Baud rate:	9600, 19200 and 38400 baud

A serial interface (RS-232) is available through terminal blocks 16, 17 and 18. It can be configured in the **Serial** menu, see the "6.13 Serial menu" section on page 61.

The RS-232 serial interface can be used:

- for easy setup and commissioning of the unit
- to modify settings and parameters during operation
- to read out internal states and current measuring values via PC or PLC

The following drawing shows the connection to a PC by using a standard D-Sub 9-pin connector:



4.9 Control outputs (AVI and DO order codes)

Control outputs technical specifications

Number of outputs:	4
Format / level:	5 ... 30 V (depending on the voltage level provided to terminal block 19 - COM+), PNP
Output current:	max. 200 mA
Reaction time:	< 1 ms


Four control outputs are available at terminal blocks 20, 21, 22 and 23 (+ terminal block 19 for switching voltage).

The switching conditions can be set in the **Preselection 1 ... Preselection 4** menus, see the "6.9 Preselection 1 menu" ... "6.12 Preselection 4 menu" sections on pages 51, 55, 57 and 59 respectively. The outputs "20 - Ctrl. Out 1", "21 - Ctrl. Out 2", "22 - Ctrl. Out 3" and "23 - Ctrl. Out 4" are fast PNP outputs with a switching capability of 5÷30 V / 200 mA per channel. The switching states are displayed (display with unit and status bar) as **C1** ... **C4**, see the "5 - Display and touch screen" section on page 26.

The switching voltage of the outputs must be applied to input terminal block 19 (COM+).

In case of switching inductive loads it is advisable to use an external filtering of the coils.

4.9.1 Wiring of the control outputs



4.10 Relay outputs (RO order code)

Relay outputs technical specifications

Number of outputs:	2
Configuration:	potential-free changeovers
AC switching capacity:	max. 250 Vac / 3 A / 750 VA
DC switching capacity:	max. 150 Vdc / 2 A / 50 W
Reaction time:	< 20 ms


Two relay outputs with potential-free changeover contacts are available at terminal blocks 27, 28, 29, 30, 31 and 32. The switching conditions can be set in the **Preselection 1 ... Preselection 4** menus, see the "6.9 Preselection 1 menu" ... "6.12 Preselection 4 menu" sections on pages 51, 55, 57 and 59 respectively.

The switching states are displayed (display with unit and status bar) as **K1** and **K2**, see the "5 - Display and touch screen" section on page 26.

AC switching capacity max. 250 Vac / max. 3 A / 750 VA

DC switching capacity max. 150 Vdc / max. 2 A / 50 W

4.10.1 Wiring of the relay outputs



5 – Display and touch screen

5.1 Screen structure for parametrization

Menus and parameters are described in the "6 – Menus and parameters" section on page 28.



Start setup procedure

To enter the menus and edit the parameters, keep the touchscreen pressed for 3 seconds.



Selection of the menu

Select the menu by pressing the arrow keys and confirm the choice by pressing the **ok** key.

You can exit the selection of the menu by pressing the **C** key.



Selection of the parameter

Select the parameter by pressing the arrow keys and confirm the choice by pressing the **ok** key.

You can exit the selection of the parameter by pressing the **C** key.



Parameter setting:

After selection the parameter (or its last digit) starts blinking. Set the parameter by pressing the **↑** and **↓** arrow keys, shift the cursor by pressing the **←** and **→** arrow keys and save the value by pressing the **ok** key.

You can exit the editing of the parameter by pressing the **C** key.

Parameter changes become active only after closing the selection of the menu.

5.2 Screen structure during operation

The following screens are available during operation. Depending on the device version and the selected operation mode, not all displays will be shown.



Display with unit and status bar

To switch to the next display, press the touch screen.

Control output states and relay states are only shown with AVI, DO and RO order codes.



Display batch counter

To switch to the next display, press the top half of the screen.

It is available only when the **Batch mode** is active.




Display with command keys

To switch to the next display, press the top half of the screen.

It is available only when the **Timer** or **Counter** operation modes are active.




Display for quick start of the preselection values setting process (see the "6.8 Preselection values menu" section on page 50)

To switch to the next display, press the top half of the screen or the  key.

It is available only with AVI, DO and RO order codes.



Display with current, minimum and maximum values.

To switch to the next display, press the top half of the screen or the  key.

6 – Menus and parameters

6.1 Overview of the structure

The following tables offer an overview of the menus and their relevant parameters. The menu names are printed in bold and the associated parameters are listed under the menu name. Depending on the device model and the selected operation mode, only the available menus / parameters are shown.



NOTE

In the pages that describe the menus, the default values are highlighted with grey background.

General menu , see the "6.2 General menu" section on page 33
Operational mode , see on page 33
Encoder properties LD350 , see on page 33 (LD350 model) or Encoder properties LD355 , see on page 33 (LD355 model)
Encoder supply , see on page 34
Counting direction , see on page 34
Scale units , see on page 34
Linearization mode , see on page 35
Pin preselection , see on page 36
Pin parameter , see on page 36
Back up memory , see on page 36
Factory settings , see on page 36

The following menus depend on the setting of the **Operational mode** parameter, see on page 33.

Operational mode = SPEED, Speed operation mode menu , see the "6.3 Speed operation mode menu" section on page 37
Display value , see on page 37
Base frequency (Hz) , see on page 37
Decimal point , see on page 37
Sampling time (s) , see on page 38
Wait time (s) , see on page 38
Standstill time (s) , see on page 39
Average filter , see on page 39
For/Rev detection , see on page 39

Operational mode = PROCESS TIME, **Process Time operation mode menu**, see the "6.4 Process Time operation mode menu" section on page 40

Display format, see on page 40

Display value, see on page 40

Base frequency (Hz), see on page 40

Sampling time (s), see on page 41

Wait time (s), see on page 41

Standstill time (s), see on page 42

Average filter, see on page 42

Operational mode = TIMER, **Timer operation mode menu**, see the "6.5 Timer operation mode menu" section on page 43

Time base, see on page 43

Start / Stop, see on page 43

Latch function, see on page 44

Set value, see on page 44

Inc / Dec mode, see on page 44

Operational mode = COUNTER, **Counter operation mode menu**, see the "6.6 Counter operation mode menu" section on page 45

Count mode, see on page 45

Factor, see on page 45

Set value, see on page 46

Decimal point, see on page 46

Batch mode, see on page 46

Batch set value, see on page 47

Operational mode = VELOCITY, **Velocity operation mode menu**, see the "6.7 Velocity operation mode menu" section on page 48

Start / Stop, see on page 48

Display value, see on page 48

Base time (s), see on page 48

Decimal point, see on page 48

Wait time (s), see on page 49

Standstill time (s), see on page 49

It is only available for devices with order codes AVI, DO or RO.

Preselection values menu, see the "6.8 Preselection values menu" section on page 50

Preselection 1, see on page 50

Preselection 2, see on page 50

Preselection 3, see on page 50

Preselection 4, see on page 50

It is only available for devices with order codes AVI, DO or RO.

Preselection 1 menu, see the "6.9 Preselection 1 menu" section on page 51

Mode 1, see on page 51

Hysteresis 1, see on page 53

Pulse time 1 (s), see on page 53

Output target 1, see on page 53

Output polarity 1, see on page 53

Output lock 1, see on page 54

Start up delay 1 (s), see on page 54

Event color 1, see on page 54

It is only available for devices with order codes AVI, DO or RO.

Preselection 2 menu, see the "6.10 Preselection 2 menu" section on page 55

Mode 2, see on page 55

Hysteresis 2, see on page 55

Pulse time 2 (s), see on page 55

Output target 2, see on page 55

Output polarity 2, see on page 55

Output lock 2, see on page 55

Start up delay 2 (s), see on page 56

Event color 2, see on page 56

It is only available for devices with order codes AVI, DO or RO.

Preselection 3 menu , see the "6.11 Preselection 3 menu" section on page 57
Mode 3 , see on page 57
Hysteresis 3 , see on page 57
Pulse time 3 (s) , see on page 57
Output target 3 , see on page 57
Output polarity 3 , see on page 57
Output lock 3 , see on page 57
Start up delay 3 (s) , see on page 58
Event color 3 , see on page 58

It is only available for devices with order codes AVI, DO or RO.

Preselection 4 menu , see the "6.12 Preselection 4 menu" section on page 59
Mode 4 , see on page 59
Hysteresis 4 , see on page 59
Pulse time 4 (s) , see on page 59
Output target 4 , see on page 59
Output polarity 4 , see on page 59
Output lock 4 , see on page 60
Start up delay 4 (s) , see on page 60
Event color 4 , see on page 60

It is only available for devices with order codes AVI and DO.

Serial menu , see the "6.13 Serial menu" section on page 61
Unit number , see on page 61
Serial baud rate , see on page 61
Serial format , see on page 61
Serial init , see on page 62
Serial protocol , see on page 62
Serial timer (s) , see on page 63
Serial value , see on page 63

It is only available for devices with order code AVI.

Analog menu , see the "6.14 Analog menu" section on page 64
Analog format , see on page 64
Analog start , see on page 64
Analog end , see on page 64
Analog gain (%) , see on page 65
Analog offset , see on page 65

Command menu , see the "6.15 Command menu" section on page 66
Input 1 action , see on page 66
Input 1 config. , see on page 68
Input 2 action , see on page 68
Input 2 config. , see on page 68
Input 3 action , see on page 68
Input 3 config. , see on page 68

Display menu , see the "6.16 Display menu" section on page 69
Color , see on page 69
Brightness (%) , see on page 69
Contrast , see on page 69
Screen saver (s) , see on page 69
Up-date time (s) , see on page 70
Font , see on page 70

It is only available if the **Linearization mode** parameter in the **General** menu (see on page 35) is set to either "1 – 1 QUADRANT" or "2 – 4 QUADRANT".

Linearization menu , see the "6.17 Linearization menu" section on page 71
P1(X) , see on page 71
...
P24(X) , see on page 71
P1(Y) , see on page 71
...
P24(Y) , see on page 71

6.2 General menu

The default values are highlighted with grey background.

Operational mode

This parameter allows to set the required operational mode, i.e. the desired measuring function.

0	SPEED	Speed indicator (RPM), tachometer or frequency counter, see the "6.3 Speed operation mode menu" section on page 37.
1	PROCESS TIME	Operation as baking time or processing time indicator (reciprocal speed), see the "6.4 Process Time operation mode menu" section on page 40.
2	TIMER	Operation as stopwatch, see the "6.5 Timer operation mode menu" section on page 43.
3	COUNTER	Operation as position indicator, event, sum, differential or up-down counter, see the "6.6 Counter operation mode menu" section on page 45.
4	VELOCITY	Runtime measurement as speed indicator, see the "6.7 Velocity operation mode menu" section on page 48.

Encoder properties LD350

This parameter is only available for LD350 model.

It allows to set the characteristics of the pulse inputs for LD350.

0	PNP	PNP (switch to +)
1	NPN	NPN (switch to -)
2	NAMUR	Connect sensor (-) to GND and sensor (+) to input (A or B)
3	TRI-STATE	Tri-State for Push-Pull encoders / sensors

Encoder properties LD355

This parameter is only available for LD355 model.

It allows to set the characteristics of the pulse inputs for LD355.

0	RS422	RS-422 standard
1	HTL DIFFERENTIAL	HTL differential
2	HTL PNP	HTL PNP single ended (switch to +)
3	HTL NPN	HTL NPN single ended (switch to -)

Encoder supply

This parameter is only available for LD355 model.

It allows to set the voltage level of the auxiliary voltage output (4 = Aux. Out). For more information refer to the "4.3 Auxiliary voltage output" section on page 18.

0	24VDC SUPPLY	24 Vdc encoder supply
1	5VDC SUPPLY	5 Vdc encoder supply

Counting direction

This parameter is only available when the **Counter** operation mode is active, see the "6.6 Counter operation mode menu" section on page 45.

It allows to set the counting direction: the display will show the count up information when the encoder rotates clockwise / counter-clockwise (or the axis moves forward / backward).

0	FORWARD	Clockwise / Forward direction
1	REVERSE	Counter-clockwise / Reverse direction

Scale units

This parameter sets the required engineering unit. It does not affect the calculation of the display value. The number of decimal places must be set in the **Decimal point** parameter that is available in each specific operation mode menu.

0	Hz	Default when Speed operation menu is active
1	kHz	
2	m/s	
3	m/min	
4	km/h	
5	mph	
6	1/min	
7	RPM	
8	1/sec	
9	RPS	
10	Stk/h	
11	pcs/h	
12	mm	
13	m	
14	inch	

15	feet																																																																																																	
16	Stueck																																																																																																	
17	pcs																																																																																																	
18	sec	Default when Process time , Timer , Counter and Velocity operation menus are active																																																																																																
19	min																																																																																																	
20	Min:Sec																																																																																																	
21	H:M:S																																																																																																	
22	%																																																																																																	
23	l/min																																																																																																	
24	gal/min																																																																																																	
25	ml/min																																																																																																	
26	gr/min																																																																																																	
27	inch/min																																																																																																	
28	H:M																																																																																																	
29	Edit unit	A customized measuring unit with up to 16 digits can be edited using this parameter. When you press the  key the Edit Unit menu appears. A measuring unit can be created using the arrow keys (by pressing and holding the arrow key down the characters scroll fast). Press the  key to save the Edit Unit menu. Press the  key to close the Edit Unit menu. <table><tr><td></td><td>!</td><td>"</td><td>#</td><td>\$</td><td>%</td><td>&</td><td>'</td><td>(</td><td>)</td><td>*</td><td>+</td><td>,</td><td>-</td><td>.</td><td>/</td></tr><tr><td>0</td><td>1</td><td>2</td><td>3</td><td>4</td><td>5</td><td>6</td><td>7</td><td>8</td><td>9</td><td>:</td><td>;</td><td><</td><td>=</td><td>></td><td>?</td></tr><tr><td>@</td><td>A</td><td>B</td><td>C</td><td>D</td><td>E</td><td>F</td><td>G</td><td>H</td><td>I</td><td>J</td><td>K</td><td>L</td><td>M</td><td>N</td><td>O</td></tr><tr><td>P</td><td>Q</td><td>R</td><td>S</td><td>T</td><td>U</td><td>V</td><td>W</td><td>X</td><td>Y</td><td>Z</td><td>[</td><td>\</td><td>]</td><td>^</td><td>_</td></tr><tr><td>`</td><td>a</td><td>b</td><td>c</td><td>d</td><td>e</td><td>f</td><td>g</td><td>h</td><td>i</td><td>j</td><td>k</td><td>l</td><td>m</td><td>n</td><td>o</td></tr><tr><td>p</td><td>q</td><td>r</td><td>s</td><td>t</td><td>u</td><td>v</td><td>w</td><td>x</td><td>y</td><td>z</td><td>{</td><td> </td><td>}</td><td>~</td><td></td></tr></table>		!	"	#	\$	%	&	'	(	)	*	+	,	-	.	/	0	1	2	3	4	5	6	7	8	9	:	;	<	=	>	?	@	A	B	C	D	E	F	G	H	I	J	K	L	M	N	O	P	Q	R	S	T	U	V	W	X	Y	Z	[	\	]	^	_	`	a	b	c	d	e	f	g	h	i	j	k	l	m	n	o	p	q	r	s	t	u	v	w	x	y	z	{		}	~	
	!	"	#	\$	%	&	'	(	)	*	+	,	-	.	/																																																																																			
0	1	2	3	4	5	6	7	8	9	:	;	<	=	>	?																																																																																			
@	A	B	C	D	E	F	G	H	I	J	K	L	M	N	O																																																																																			
P	Q	R	S	T	U	V	W	X	Y	Z	[	\	]	^	_																																																																																			
`	a	b	c	d	e	f	g	h	i	j	k	l	m	n	o																																																																																			
p	q	r	s	t	u	v	w	x	y	z	{		}	~																																																																																				

Linearization mode

This parameter activates and sets the linearisation function. See the "6.17 Linearization menu" section on page 71 and the "6.17.1 Description of the linearisation function" section on page 71.

0	OFF	No linearisation
1	1 QUADRANT	Linearisation using 1 quadrant (see on page 71).
2	4 QUADRANT	Linearisation using 4 quadrants (see on page 71).

Pin preselection

This parameter allows to set the PIN code to lock the quick start of the **Preselection values** menu used to enter the preselection values, see the "5.2 Screen structure during operation" section on page 27. Refer also to the "6.8 Preselection values menu" section on page 50. Master PIN is 6079.

This lock function is only useful if used along with the lock function set in the **Pin parameter**.

0000	No lock
...	
9999	Access after entering PIN Code 9999

Pin parameter

This parameter sets the PIN code for lock function of all parameters. The Master PIN is 6079.

0000	No lock
...	
9999	Parametrization of the unit after entering PIN code 9999

Back up memory

0	NO	No memory backup following a power failure
1	YES	Backup memory following a power failure, the current values will be saved

Factory settings

At any time you can return all settings to the factory default values.

Default values are highlighted with **grey background** in this manual.



WARNING

This action will reset all parameters to factory default values and customised settings will be lost. After reset you will have to repeat your individual set-up procedure.

0	NO	No default values are loaded
1	YES	Load default values of all parameters

6.3 Speed operation mode menu

When the **Operational mode** parameter in the **General** menu is set to 0 = SPEED (see on page 33), the **Speed operation mode** menu is available. It allows to set the unit operation as speed indicator (RPM), tachometer or frequency meter.

In this operation mode only input A is active or input A and input B with 90° phase offset for detection of forward / reverse motion.

Display value

Desired value that will be displayed according to the setting of the **Base frequency (Hz)** parameter.

00000001	Smallest value
0000100.0	Default value
99999999	Highest value

Base frequency (Hz)

Reference frequency for the desired **Display value** expressed in Hz.

000001	Smallest value
000100	Default value
500000	Highest value

Decimal point


It sets the position of the decimal point.

0	NO	No decimal point
1	0000000.0	Decimal point placed in the specified position
2	000000.00	Decimal point placed in the specified position
3	00000.000	Decimal point placed in the specified position
4	0000.0000	Decimal point placed in the specified position
5	000.00000	Decimal point placed in the specified position
6	00.000000	Decimal point placed in the specified position
7	0.0000000	Decimal point placed in the specified position

Sampling time (s)

It allows to set the minimum measurement time. This parameter is used as a filter in case of uneven frequencies. It directly affects the response time of the unit. The value is expressed in seconds (s).


0.005	Shortest Sampling time
0.100	Default value
9.999	Longest Sampling time



Wait time (s)

This parameter sets the span of time of the lowest frequency, i.e. the time between two rising edges when the device detects the frequency 0 Hz. Frequencies whose span of time is longer than the set **Wait time (s)** will be evaluated as frequency = 0 Hz. The value is expressed in seconds (s).

0.01	Frequency = 0 Hz, for frequencies below 100 Hz
01.00	Default value
99.99	Frequency = 0 Hz, for frequencies below 0.1 Hz



Standstill time (s)

This parameter sets the time after which a standstill condition is acknowledged. When the "frequency = 0 Hz" condition is detected, after the delay set next to this parameter the unit warns of the standstill condition and reactivates the start up delays (see the **Start up delay x (s)** parameter in the **Preselection 1 ... Preselection 4** menus on pages 51, 55, 57 and 59 respectively).

Standstill detection can be set in the **Preselection 1 ... Preselection 4** menus, see on pages 51, 55, 57 and 59 respectively.

00.00	Shortest time
...	
99.99	Longest time

Average filter

Selectable average or filter function to avoid measuring fluctuations due to unstable frequencies. With settings 1 to 4 a floating average calculation is performed. With settings 5 to 8, the device uses an exponential filter. The time constant T (63%) corresponds to the number of sampling cycles.



EXAMPLE

If **Sampling time (s)** = 0.1 s and **Average filter** = "Exponential filter, T (63 %) = 2x **Sampling time (s)**", after 0.2 seconds, 63% of the step size is reached.

0	OFF	No average value will be created
1	2 cycle average	Floating average within 2 cycles
2	4 cycle average	Floating average within 4 cycles
3	8 cycle average	Floating average within 8 cycles
4	16 cycle average	Floating average within 16 cycles
5	2 cycle filter	Exponential filter, T (63 %) = 2x Sampling time (s)
6	4 cycle filter	Exponential filter, T (63 %) = 4x Sampling time (s)
7	8 cycle filter	Exponential filter, T (63 %) = 8x Sampling time (s)
8	16 cycle filter	Exponential filter, T (63 %) = 16x Sampling time (s)

For/Rev detection

This parameter enables the detection of the direction of rotation (input A, input B with 90° phase shift).

0	NO	Detection of the direction of rotation OFF
1	YES	Detection of the direction of rotation ON

6.4 Process Time operation mode menu

When the **Operational mode** parameter in the **General** menu is set to 1 = PROCESS TIME (see on page 33), the **Process Time operation mode** menu is available. It allows to set the unit operation as baking time or processing time indicator (reciprocal speed).

Only input A is used.

Display format

This parameter sets the display format for the value. The corresponding decimal point will be set automatically.

0	SECONDS	Value displayed in seconds
1	MINUTES	Value displayed in minutes
2	MIN:SEC	Value displayed in Minutes : Seconds
3	MIN.00	Value displayed in Minutes . Hundredths of a minute (1/100)
4	H:M:S	Value displayed in Hours : Minutes : Seconds

Display value

Desired value that will be displayed according to the setting of the **Base frequency (Hz)** parameter.

00000001	Smallest value
00001000	Default value
99999999	Highest value

Base frequency (Hz)


Reference frequency for the desired **Display value** expressed in Hz.

000001	Smallest value
000100	Default value
500000	Highest value

Sampling time (s)

It allows to set the minimum measurement time. This parameter is used as a filter in case of uneven frequencies. It directly affects the response time of the unit. The value is expressed in seconds (s).


0.005	Shortest Sampling time
0.100	Default value
9.999	Longest Sampling time



Wait time (s)

This parameter sets the span of time of the lowest frequency, i.e. the time between two rising edges when the device detects the frequency 0 Hz. Frequencies whose span of time is longer than the set **Wait time (s)** will be evaluated as frequency = 0 Hz. The value is expressed in seconds (s).

00.01	Frequency = 0 Hz, for frequencies below 100 Hz
01.00	Default value
99.99	Frequency = 0 Hz, for frequencies below 0.1 Hz



Standstill time (s)

This parameter sets the time after which a standstill condition is acknowledged. When the "frequency = 0 Hz" condition is detected, after the delay set next to this parameter the unit warns of the standstill condition and reactivates the start up delays (see the **Start up delay x (s)** parameter in the **Preselection 1 ... Preselection 4** menus on pages 51, 55, 57 and 59 respectively).

Standstill detection can be set in the **Preselection 1 ... Preselection 4** menus, see on pages 51, 55, 57 and 59 respectively.

00.00	Shortest time
...	
99.99	Longest time

Average filter

Selectable average or filter function to avoid measuring fluctuations due to unstable frequencies. With settings 1 to 4 a floating average calculation is performed. With settings 5 to 8, the device uses an exponential filter. The time constant T (63%) corresponds to the number of sampling cycles.



EXAMPLE

If **Sampling time (s)** = 0.1 s and **Average filter** = "Exponential filter, T (63 %) = 2x **Sampling time (s)**", after 0.2 seconds, 63% of the step size is reached.

0	OFF	No average value will be created
1	2 cycle average	Floating average within 2 cycles
2	4 cycle average	Floating average within 4 cycles
3	8 cycle average	Floating average within 8 cycles
4	16 cycle average	Floating average within 16 cycles
5	2 cycle filter	Exponential filter, T (63 %) = 2x Sampling time (s)
6	4 cycle filter	Exponential filter, T (63 %) = 4x Sampling time (s)
7	8 cycle filter	Exponential filter, T (63 %) = 8x Sampling time (s)
8	16 cycle filter	Exponential filter, T (63 %) = 16x Sampling time (s)

6.5 Timer operation mode menu

When the **Operational mode** parameter in the **General** menu is set to 2 = TIMER (see on page 33), the **Timer operation mode** menu is available. It allows to set the unit operation as timer or stopwatch.

Depending on the parametrization only input A or both inputs A and B are used.

Time base

This parameter sets the time base or resolution of the measurement.

0	1/1000 SEC	Milliseconds
1	1/100 SEC	Hundredths of a second (1/100)
2	1/10 SEC	Tenths of a second (1/10)
3	SECONDS	Full seconds
4	MIN.00	Minutes and hundredths of a minute (1/100)
5	MIN.0	Minutes and tenths of a minute (1/10)
6	H:M:S	Hours : Minutes : Seconds (9999:59:59)
7	H:M	Hours : Minutes (999999:59)

Start / Stop

This parameter sets the start/stop condition of the time measurement.

0	COUNT AT A HIGH	Time measurement is active as long as input A signal is "HIGH"
1	COUNT AT A LOW	Time measurement is active as long as input A signal is "LOW"
2	START A / STOP B	A rising edge of input A signal starts the time measurement; a rising edge of input B signal stops the time measurement
3	PERIODE AT A	Time period measurement: the span of time between two rising edges of input A signal is displayed

Auto set / reset

0	NO	Time measurement operates by adding up or subtracting measured values (see the Inc / Dec mode parameter in the next page), no automatic set / reset operation is carried out at next start. Start setting must be done via set / reset (see "6.15 Command menu" section on page 66)
---	----	--

1	YES	At each start, the new time measurement automatically starts from the value set next to the Set value parameter (see the next page)
---	-----	--

Latch function

0	NO	Real time display, the counting value appears on the display
1	YES	The display shows the result of the last measurement; the current measurement is shown in the background

Set value

In case of a set / reset command (via keyboard shortcut, control input or PC user interface), the timer is preset to the value entered next to this item. See also the **Auto set / reset** parameter in the previous page.

00000.000	Smallest value (Reset)
...	
99999999	Highest value

Inc / Dec mode

It sets the time measurement operation by adding or subtracting measured values. When the **Start / Stop** parameter is set to 3 = PERIODE AT A (period time measurement), the time measurement always operates by adding measured values.

0	INCREMENT MODE	Time measurement operates by adding measured values
1	DECREMENT MODE	Time measurement operates by subtracting measured values

6.6 Counter operation mode menu

When the **Operational mode** parameter in the **General** menu is set to 3 = COUNTER (see on page 33), the **Counter operation mode** menu is available. It allows to set the unit operation as position indicator, impulse counter, 2 inputs sum counter, 2 inputs differential counter or up-down counter. Input A and input B are both used.

Count mode

This parameter allows to set the counter operational mode.

0	A SINGLE	Input A is used as counting input. Input B is used to set the counting direction: "LOW" = Clockwise / Forward direction; "HIGH" = Counter-clockwise / Reverse direction
1	A + B	Sum counter: A channel pulses + B channel pulses
2	A - B	Differential counter: A channel pulses - B channel pulses
3	A/B 90 x1	Quadrature counter: Pulses A, B with edge counting x1
4	A/B 90 x2	Quadrature counter: Pulses A, B with edge counting x2
5	A/B 90 x4	Quadrature counter: Pulses A, B with edge counting x4

Factor

It sets the scaling factor. When the sum counter mode (**Count mode** = 1 = A + B) or the differential counter mode (**Count mode** = 2 = A - B) are set, please note that the pulse scaling factor will only affect input A.



EXAMPLE

If **Factor** is set to 1.23456, 100,000 input pulses will result in a value of 123456.

00.00001	Smallest value
01.00000	Default value
99.99999	Highest value

Set value

In case of a reset command (via keyboard shortcut, control input, or PC user interface), the counter is set to the value entered next to this item.

-99999999	Smallest value
+00000000	Default value
+99999999	Highest value

Decimal point

This parameter sets the position of the decimal point.

0	NO	No decimal point
1	0000000.0	Decimal point placed in the specified position
2	000000.00	Decimal point placed in the specified position
3	00000.000	Decimal point placed in the specified position
4	0000.0000	Decimal point placed in the specified position
5	000.00000	Decimal point placed in the specified position
6	00.000000	Decimal point placed in the specified position
7	0.0000000	Decimal point placed in the specified position

Batch mode

It allows to set the batch counter.

The function of batch counting according to a preset value (**Preselection 1 ... Preselection 3**) is only possible if the switch conditions "automatic reset to zero" ($7 = \text{RESULT} \geq \text{PRES} \rightarrow 0$) or "set the counter value" ($8 = \text{RESULT} \leq 0 \rightarrow \text{SET}$) are enabled.

Preselection 4 value is the preset value of the batch counter, when the **Batch mode** is active.



EXAMPLE

We need the batch counter to increment by 1 at each 1,000 pulses.

Preselection 1 parameter has to be set to "1000"; the corresponding switch condition **Mode 1** has to be set to " $7 = \text{RESULT} \geq \text{PRES} \rightarrow 0$ "; **Batch mode** has to be set to "**1 = INCREMENT BATCH**". Should an output be turned on after a batch amount of 33, **Preselection 4** has to be set to "33" and the switching condition of **Mode 4** has to be set to "display value greater than or equal to" ($3 = \text{RESULT} \geq \text{PRES}$).

0	OFF	No batch counter
---	-----	------------------

1	INCREMENT BATCH	Batch counter operates by incrementing
2	DECREMENT BATCH	Batch counter operates by decrementing
3	USE INPUTS ONLY	The batch counter is operated only via external commands (see the Command menu, refer to the "6.15 Command menu" section on page 66)

Batch set value

In case of a reset / set command (via keyboard, control input or PC user interface) the batch counter is set to the value entered next to this item. The parameter is available only when the **Batch mode** is active.

00000000	Smallest value
...	
99999999	Highest value

6.7 Velocity operation mode menu

When the **Operational mode** parameter in the **General** menu is set to 4 = VELOCITY (see on page 33), the **Velocity operation mode** menu is available. It allows to set the unit operation as runtime measurement for speed. Channel A is the start input while channel B is the stop input.

Start / Stop

This parameter sets the start and stop condition.

0	RISE TO RISE	Start = rising edge of input A signal Stop = rising edge of input B signal
1	FALL TO FALL	Start = falling edge of input A signal Stop = falling edge of input B signal
2	RISE TO FALL	Start = rising edge of input A signal Stop = falling edge of input B signal
3	FALL TO RISE	Start = falling edge of input A signal Stop = rising edge of input B signal

Display value

Desired value that will be displayed according to the setting of the **Base time (s)** parameter.

00000001	Smallest value
00001000	Default value
99999999	Highest value

Base time (s)

Reference time for the desired **Display value** expressed in seconds.

000.001	Smallest value
001.000	Default value
999.999	Highest value

Decimal point

This parameter sets the position of the decimal point.


0	NO	No decimal point
1	0000000.0	Decimal point placed in the specified position
2	000000.00	Decimal point placed in the specified position
3	00000.000	Decimal point placed in the specified position

4	0000.0000	Decimal point placed in the specified position
5	000.00000	Decimal point placed in the specified position
6	00.000000	Decimal point placed in the specified position
7	0.0000000	Decimal point placed in the specified position

Wait time (s)

This parameter sets the span of time of the lowest frequency, i.e. the time between two rising edges when the device detects the frequency 0 Hz. Frequencies whose span of time is longer than the set **Wait time (s)** will be evaluated as frequency = 0 Hz. The value is expressed in seconds (s).

00.00	The display value is retained until a new value is available
00.01	Frequency = 0 Hz, for frequencies below 100 Hz
...	
99.99	Frequency = 0 Hz, for frequencies below 0.1 Hz



Standstill time (s)

This parameter sets the time after which a standstill condition is acknowledged. When the "frequency = 0 Hz" condition is detected, after the delay set next to this parameter the unit warns of the standstill condition and reactivates the start up delays (see the **Start up delay x (s)** parameter in the **Preselection 1 ... Preselection 4** menus on pages 51, 55, 57 and 59 respectively).

Standstill detection can be set in the **Preselection 1 ... Preselection 4** menus, see on pages 51, 55, 57 and 59 respectively.

Standstill time (s) makes sense only if **Wait time (s)** parameter is different from 00.00.

00.00	Shortest time
...	
99.99	Longest time

6.8 Preselection values menu

The **Preselection values** menu is used to set the preselection values or the switching points.

The preselection values / switching points are always referred to the display value.

This menu is only available for devices with order codes AVI, DO or RO.

Preselection 1

Preselection / switching point 1. The features of **Preselection 1** must be set in the **Preselection 1** menu, see "6.9 Preselection 1 menu" section on page 51.

-9999999.9	Smallest value
+0000100.0	Default value
+9999999.9	Highest value

Preselection 2

Preselection / switching point 2. The features of **Preselection 2** must be set in the **Preselection 2** menu, see "6.10 Preselection 2 menu" section on page 55.

-9999999.9	Smallest value
+0000200.0	Default value
+9999999.9	Highest value

Preselection 3

Preselection / switching point 3. The features of **Preselection 3** must be set in the **Preselection 3** menu, see "6.11 Preselection 3 menu" section on page 57.

-9999999.9	Smallest value
+0000300.0	Default value
+9999999.9	Highest value

Preselection 4

Preselection / switching point 4. The features of **Preselection 4** must be set in the **Preselection 4** menu, see "6.12 Preselection 4 menu" section on page 59.

When the **Batch mode** is active (see on page 46), **Preselection 4** value is the preset value of the batch counter.

-9999999.9	Smallest value
+0000400.0	Default value
+9999999.9	Highest value

6.9 Preselection 1 menu

The **Preselection 1** menu is only available for devices with order codes AVI, DO and RO. It allows to set the characteristics of **Preselection 1**.

Mode 1

Switching conditions for **Preselection 1**. The output / relay / display switches under the following conditions:

0	$ \text{RESULT} \geq \text{PRES} $	The absolute display value is greater than or equal to the absolute value of Preselection 1. If Hysteresis 1 is greater than 0, the following switching condition is applied: Display value $\geq$ Preselection 1 → ON Display value $<$ Preselection 1 - Hysteresis 1 → OFF
1	$ \text{RESULT} \leq \text{PRES} $	The absolute display value is less than or equal to the absolute value of Preselection 1 (start up suppression – see the Start up delay 1 (s) parameter on page 54– is advisable). If Hysteresis 1 is greater than 0, the following switching condition is applied: Display value $\leq$ Preselection 1 → ON Display value $>$ Preselection 1 + Hysteresis 1 → OFF
2	$ \text{RESULT} = \text{PRES} $	The absolute display value is equal to the absolute value of Preselection 1. A range (Preselection 1 $\pm$ $\frac{1}{2}$ Hysteresis 1) can be defined and monitored along with a hysteresis value. If Hysteresis 1 is greater than 0, the following switching condition is applied: Display value $>$ Preselection 1 + $\frac{1}{2}$ Hysteresis 1 → OFF Display value $<$ Preselection 1 - $\frac{1}{2}$ Hysteresis 1 → OFF
3	$\text{RESULT} \geq \text{PRES}$	Display value is greater than or equal to Preselection 1, e.g. an overspeed is detected. If Hysteresis 1 is greater than 0, the following switching condition is applied: Display value $\geq$ Preselection 1 → ON Display value $<$ Preselection 1 - Hysteresis 1 → OFF
4	$\text{RESULT} \leq \text{PRES}$	Display value is less than or equal to Preselection 1, e.g. an underspeed is detected (start up suppression –see the Start up delay 1 (s) parameter on page 54– is advisable). If Hysteresis 1 is greater than 0, the following

		switching condition is applied: Display value $\leq$ Preselection 1 $\rightarrow$ ON Display value $>$ Preselection 1 + Hysteresis 1 $\rightarrow$ OFF
5	RESULT = PRES	Display value is equal to Preselection 1 . A range (Preselection 1 $\pm$ $\frac{1}{2}$ Hysteresis 1) can be defined and monitored along with a hysteresis value. If Hysteresis 1 is greater than 0, the following switching condition is applied: Display value $>$ Preselection 1 + $\frac{1}{2}$ Hysteresis 1 $\rightarrow$ OFF Display value $<$ Preselection 1 - $\frac{1}{2}$ Hysteresis 1 $\rightarrow$ OFF
6	RESULT = 0	Display value is zero (standstill condition detected after the Standstill time (s) delay has expired), e. g. standstill monitoring. It is only available when Speed or Process Time operation modes are selected (see on pages 37 and 40 respectively).
7	RESULT $\geq$ PRES $\rightarrow$ 0	Auto reset at Preselection 1 . It is only available when Timer or Counter operation modes are selected (see on pages 43 and 45 respectively). Display value is greater than or equal to Preselection 1 , the display value is set to 0. If Batch mode is active (see on page 46), the batch counter increments or decrements when the display value is set to 0.
8	RESULT $\leq$ 0 $\rightarrow$ SET	Auto set to Preselection 1 . It is only available when Timer or Counter operation modes are selected (see on pages 43 and 45 respectively). Display value is less than or equal to 0, the display value is set to Preselection 1 . If Batch mode is active (see on page 46), the batch counter increments or decrements when the display value is set to Preselection 1 .
9	RES $\geq$ PRES-TRAIL	Trailing Preselection 1 : Display value is greater than or equal to Preselection 2 - Preselection 1 $\rightarrow$ ON Preselection 1 is the trailing preselection from Preselection 2 .

Hysteresis 1

This parameter sets the switching hysteresis of the switch-off point for **Preselection 1** value.

000.0	No switching hysteresis
...	
99999	Switching hysteresis = 99999

Pulse time 1 (s)

Duration of the output pulse for the switching condition of **Preselection 1** value.

00.000	No output pulse (static signal)
...	
60.000	Pulse duration = 60 seconds

Output target 1

Assignment of an output or relay for the switching condition of **Preselection 1** value.

If more than one switching condition is assigned to the output / relay, the output is set when one switching condition at least is true.

0	NO	No switching condition assigned
1	CTRL OUT 1	Switching condition assigned to "20 - Ctrl. Out 1"
2	CTRL OUT 2	Switching condition assigned to "21 - Ctrl. Out 2"
3	CTRL OUT 3	Switching condition assigned to "22 - Ctrl. Out 3"
4	CTRL OUT 4	Switching condition assigned to "23 - Ctrl. Out 4"
5	RELAY 1	Switching condition assigned to "27-28-29 - Rel. 1"
6	RELAY 2	Switching condition assigned to "30-31-32 - Rel. 2"

Output polarity 1

Polarity for the switching condition of **Preselection 1**.

0	ACTIVE HIGH	Switching condition is true → Active "HIGH"
1	ACTIVE LOW	Switching condition is true → Active "LOW"

Output lock 1

Latch for the switching condition of **Preselection 1**.

0	NO	No latch for Preselection 1
1	YES	Latch for Preselection 1 (command 4 - LOCK RELEASE -see the Input 1 action parameter on page 66- will clear the latch).

Start up delay 1 (s)

Start up suppression for the switching condition of **Preselection 1**.

This adjustment only applies to the switching conditions **1 - |RESULT|<=|PRES|** and **4 - RESULT<=PRES** (see the **Mode 1** parameter on page 51) and when **Speed** or **Process Time** operation modes are selected (see on pages 37 and 40 respectively).

00.000	No start up suppression
...	
60.000	Start up suppression expressed in seconds



NOTE

Start up delay 3 (s) and **Start up delay 4 (s)** (see on pages 58 and 60 respectively) have an automatic start up suppression.

Event color 1

Event-depending change of colour of the display for the switching condition of **Preselection 1**. **Event color 1** has the lowest priority. **Event color 2**, **Event color 3** and **Event color 4** are allowed to overwrite this change of colour.

0	NO CHANGE	No change of colour
1	CHANGE TO RED	Colour of display changes to red
2	CHANGE TO GREEN	Colour of display changes to green
3	CHANGE TO YELLOW	Colour of display changes to yellow

6.10 Preselection 2 menu

The **Preselection 2** menu is only available for devices with order codes AVI, DO and RO. It allows to set the characteristics for **Preselection 2**.

Mode 2

Switching conditions for **Preselection 2**. The output / relay / display switches under the following conditions:

0 ... 8	For complete information on the switching conditions 0 ... 8, please refer to the Mode 1 parameter in the "6.9 Preselection 1 menu" section on page 51.
9 RES>=PRES-TRAIL	Trailing Preselection 2 : Display value is greater than or equal to Preselection 1 – Preselection 2 → ON Preselection 2 is the trailing preselection from Preselection 1 .

Hysteresis 2

This parameter sets the switching hysteresis of the switch-off point for **Preselection 2** value. For complete information please refer to the **Hysteresis 1** parameter in the "6.9 Preselection 1 menu" section on page 51.

Pulse time 2 (s)

Duration of the output pulse for the switching condition of **Preselection 2** value. For complete information please refer to the **Pulse time 1 (s)** parameter in the "6.9 Preselection 1 menu" section on page 51.

Output target 2

Assignment of an output or relay for the switching condition of **Preselection 2** value. For complete information please refer to the **Output target 1** parameter in the "6.9 Preselection 1 menu" section on page 51.

Output polarity 2

Polarity for the switching condition of **Preselection 2**. For complete information please refer to the **Output polarity 1** parameter in the "6.9 Preselection 1 menu" section on page 51.

Output lock 2

Latch for the switching condition of **Preselection 2**. For complete information please refer to the **Output lock 1** parameter in the "6.9 Preselection 1 menu" section on page 51.

Start up delay 2 (s)

Start up suppression for the switching condition of **Preselection 2**. For complete information please refer to the **Start up delay 1 (s)** parameter in the "6.9 Preselection 1 menu" section on page 51.



NOTE

Start up delay 3 (s) and **Start up delay 4 (s)** (see on pages 58 and 60 respectively) have an automatic start up suppression.

Event color 2

Event-dependent change of colour of the display for the switching condition of **Preselection 2**. **Event color 2**, **Event color 3** and **Event color 4** have the highest priority and are allowed to overwrite the change of colour set next to the **Event color 1** parameter. For complete information please refer to the **Event color 1** parameter in the "6.9 Preselection 1 menu" section on page 51.

6.11 Preselection 3 menu

The **Preselection 3** menu is only available for devices with order codes AVI, DO and RO. It allows to set the characteristics for **Preselection 3**.

Mode 3

Switching conditions for **Preselection 3**. The output / relay / display switches under the following conditions:

0 ... 8	For complete information on the switching conditions 0 ... 8, please refer to the Mode 1 parameter in the "6.9 Preselection 1 menu" section on page 51.
9 RES>=PRES-TRAIL	Trailing Preselection 3 : Display value is greater than or equal to Preselection 4 – Preselection 3 → ON Preselection 3 is the trailing preselection from Preselection 4 .

Hysteresis 3

This parameter sets the switching hysteresis of the switch-off point for **Preselection 3** value. For complete information please refer to the **Hysteresis 1** parameter in the "6.9 Preselection 1 menu" section on page 51.

Pulse time 3 (s)

Duration of the output pulse for the switching condition of **Preselection 3** value. For complete information please refer to the **Pulse time 1 (s)** parameter in the "6.9 Preselection 1 menu" section on page 51.

Output target 3

Assignment of an output or relay for the switching condition of **Preselection 3** value. For complete information please refer to the **Output target 1** parameter in the "6.9 Preselection 1 menu" section on page 51.

Output polarity 3

Polarity for the switching condition of **Preselection 3**. For complete information please refer to the **Output polarity 1** parameter in the "6.9 Preselection 1 menu" section on page 51.

Output lock 3

Latch for the switching condition of **Preselection 3**. For complete information please refer to the **Output lock 1** parameter in the "6.9 Preselection 1 menu" section on page 51.

Start up delay 3 (s)

Start up suppression for the switching condition of **Preselection 3**.

This adjustment only applies to the switching conditions **1** - $|\text{RESULT}| \leq |\text{PRES}|$ and **4** - $\text{RESULT} \leq \text{PRES}$ (see the **Mode 3** parameter on page 57) and when **Speed** or **Process Time** operation modes are selected (see on pages 37 and 40 respectively).

0	OFF	No start up suppression
1	AUTO	Automatic start up suppression, until the preselection value / switching point is exceeded for the first time.



NOTE

Start up delay 1 (s) and **Start up delay 2 (s)** (see on pages 54 and 56 respectively) have a time-dependent start up suppression.

Event color 3

Event-depending change of colour of the display for the switching condition of **Preselection 3**. **Event color 2**, **Event color 3** and **Event color 4** have the highest priority and are allowed to overwrite the change of colour set next to the **Event color 1** parameter. For complete information please refer to the **Event color 1** parameter in the "6.9 Preselection 1 menu" section on page 51.

6.12 Preselection 4 menu

The **Preselection 4** menu is only available for devices with order codes AVI, DO and RO. If **Batch mode** is active (see the "6.6 Counter operation mode menu" section on page 45), the batch counter is compared with the **Preselection 4** value.

Mode 4

Switching conditions for **Preselection 4**. The output / relay / display switches under the following conditions:

0 ... 8		For complete information on the switching conditions 0 ... 8, please refer to the Mode 1 parameter in the "6.9 Preselection 1 menu" section on page 51.
9	RES>=PRES-TRAIL	Trailing Preselection 4 : Display value is greater than or equal to Preselection 3 – Preselection 4 → ON Preselection 4 is the trailing preselection from Preselection 3 .

Hysteresis 4

This parameter sets the switching hysteresis of the switch-off point for **Preselection 4** value. For complete information please refer to the **Hysteresis 1** parameter in the "6.9 Preselection 1 menu" section on page 51.

Pulse time 4 (s)

Duration of the output pulse for the switching condition of **Preselection 4** value. For complete information please refer to the **Pulse time 1 (s)** parameter in the "6.9 Preselection 1 menu" section on page 51.

Output target 4

Assignment of an output or relay for the switching condition of **Preselection 4** value. For complete information please refer to the **Output target 1** parameter in the "6.9 Preselection 1 menu" section on page 51.

Output polarity 4

Polarity for the switching condition of **Preselection 4**. For complete information please refer to the **Output polarity 1** parameter in the "6.9 Preselection 1 menu" section on page 51.

Output lock 4

Latch for the switching condition of **Preselection 4**. For complete information please refer to the **Output lock 1** parameter in the "6.9 Preselection 1 menu" section on page 51.

Start up delay 4 (s)

Start up suppression for the switching condition of **Preselection 4**.

This adjustment only applies to the switching conditions **1** - $|\text{RESULT}| \leq |\text{PRES}|$ and **4** - $\text{RESULT} \leq \text{PRES}$ (see the **Mode 4** parameter on page 59) and when **Speed** or **Process Time** operation modes are selected (see on pages 37 and 40 respectively).

0	OFF	No start up suppression
1	AUTO	Automatic start up suppression, until the preselection value / switching point is exceeded for the first time.



NOTE

Start up delay 1 (s) and **Start up delay 2 (s)** (see on pages 54 and 56 respectively) have a time-dependent start up suppression.

Event color 4

Event-depending change of colour of the display for the switching condition of **Preselection 4**. **Event color 2**, **Event color 3** and **Event color 4** have the highest priority and are allowed to overwrite the change of colour set next to the **Event color 1** parameter. For complete information please refer to the **Event color 1** parameter in the "6.9 Preselection 1 menu" section on page 51.

6.13 Serial menu

The **Serial** menu allows to configure the basic settings of the serial interface (terminal blocks 16, 17 and 18). For complete information on the serial port features, please refer to the "4.8 Serial interface (AVI and DO order codes)" section on page 23.

This function is only available for devices with order codes AVI and DO.

Unit number

This parameter allows to set the address of the serial device. You can assign to the unit any address number between 11 and 99. The address must not contain any "0" because such numbers (20, 30, ...) are reserved for collective addressing (broadcast address).

11	Smallest address value
...	
99	Highest address value

Serial baud rate

This parameter allows to set the serial transmission speed (baud rate).

Available options are:

0	9600	9600 baud
1	19200	19200 baud
2	38400	38400 baud

Serial format

This parameter allows to set the bit data format.

		Data Bits	Parity Bit	Stop Bits
0	7-EVEN-1	7	even	1
1	7-EVEN-2	7	even	2
2	7-ODD-1	7	odd	1
3	7-ODD-2	7	odd	2
4	7-NONE-1	7	no	1
5	7-NONE-2	7	no	2
6	8-EVEN-1	8	even	1
7	8-ODD-1	8	odd	1
8	8-NONE-1	8	no	1
9	8-NONE-2	8	no	2

Serial init

This parameter allows to set the baud rate for the transmission of the initialization values to the OS6.0 software tool. If you set transmission values higher than 9600 baud, the duration of the initialization procedure will be shortened.

0	NO	The initialization values will be transmitted at 9600 baud. After initialization the unit will operate according to the user settings again.
1	YES	The initialization values will be transmitted according to the user defined baud rate (Serial baud rate parameter). After initialization the unit will go on operating according to the user settings again.

Serial protocol

It sets the sequence of characters to be sent when using the serial output for cyclic data transmission under time control (see the **Serial timer (s)** parameter). If you set the option "1" the unit address is removed from the string, this results in a slightly faster transmission cycle.

The transmission string will be as follows:

Option 0

UN	UN	+ / -	X	X	X	X	X	X	X	LF	CR
----	----	-------	---	---	---	---	---	---	---	----	----

Option 1

+ / -	X	X	X	X	X	X	X	LF	CR
-------	---	---	---	---	---	---	---	----	----

Where:

UN UN = serial address, e.g. "1 1". See the **Unit number** parameter in the previous page (option **0** only)

+ / - = plus / minus signs, i.e. positive / negative sign of transmitted value

X X X X X X X X = data to be transmitted according to the setting in the **Serial value** parameter

LF = line feed character

CR = carriage return character

0	Transmission string with serial address
1	Transmission string without serial address

Serial timer (s)

This parameter sets the cycle time for the cyclic transmission of data set in the **Serial value** parameter when using the serial output. The value is expressed in seconds. In case of a serial request, the cyclic transmission is stopped for 20 s.

00.000	Cyclic transmission is switched off. The unit will send data following a serial request or a "7 – Serial print" command (see the Input 1 action , Input 2 action and Input 3 action parameters on pages 66 and 68).
...	
60.000	Cycle time expressed in seconds.

Serial value

This parameter sets the value to be transmitted.

0	0	Measurement_Result
1	1	Speed_Value
2	2	Time_Result
3	3	Counter
4	4	Velocity_Speed
5	5	Batch_Counter
6	6	Minimal_Value
7	7	Maximal_Value
8	8	N.A.
9	9	N.A.

N.A. = not available

6.14 Analog menu

The **Analog** menu allows to configure the basic settings of the analogue output (terminal blocks 13 and 14 / 15).

For complete information on the analogue output features, please refer to the "4.7 Analogue output (AVI order code)" section on page 22.

This function is only available for devices with order code AVI.

Analog format

This parameter sets the characteristics of the analogue output. The analogue output is proportional to the display value.

If **Analog format** is set to "**0 = -10...10V**", when the **Counter** operation mode is active (see the "6.6 Counter operation mode menu" section on page 45) the polarity of the analogue output depends on the polarity of the display value.

0	-10...10V	-10 ... +10 V
1	0...20mA	0 ... 20 mA
2	4...20mA	4 ... 20 mA

Analog start

This parameter sets the start value of the analogue conversion. The start value corresponds to the display value for an analogue output of 0 V or 0 mA or 4 mA depending on the set **Analog format**.

-99999999	Smallest start value
+0000000.0	Default value
+99999999	Highest start value

Analog end

This parameter sets the end value of the analogue conversion. The end value corresponds to the display value for an analogue output of (+/-)10 V or 20 mA depending on the set **Analog format**.

-99999999	Smallest start value
+0001000.0	Default value
+99999999	Highest start value

Analog gain (%)

This parameter sets the maximum conversion of the analogue output expressed in percentage (%).

000.00	Smallest gain
100.00	Default value
110.00	Highest gain



EXAMPLE

If you set "102.00" next to this item the result will be a conversion of 10.2 V or 20.4 mA when the value set next to the **Analog end** parameter is reached.
If you set "95.00" next to this item the result will be a conversion of 9.5 V or 18 mA when the value set next to the **Analog end** parameter is reached.

Analog offset

This parameter sets the zero offset of the analogue output.

-99.99	Smallest offset
+00.00	Default value
+99.99	Highest offset



EXAMPLE

If you set "+00.20" next to this item the result will be an offset of 0.02 V or 0.04 mA as regards the **Analog start** value.

6.15 Command menu

The **Command** menu allows to configure the operation of the inputs "10 - Ctrl. In 1", "11 - Ctrl. In 2" and "12 - Ctrl. In 3".

For complete information on the control inputs features, please refer to the "4.6 Control inputs" section on page 21.

Input 1 action

This parameter sets the function of the input "10 - Ctrl. In 1".

0	NO	No function	
1	RESET/SET VALUE	When the Timer operation mode is active (see the "6.5 Timer operation mode menu" section on page 43): it resets the value to 0. When the Counter operation mode is active (see the "6.6 Counter operation mode menu" section on page 45): it resets / sets the value to the one set next to the Set value parameter (see on page 46). When the Velocity operation mode is active (see the "6.7 Velocity operation mode menu" section on page 48): it resets the value to 0.	(d) (s)
2	FREEZE	It freezes the current display value.	(s)
3	KEY LOCK	It disables the touch screen.	(s)
4	LOCK RELEASE	It releases the lock in all outputs / relay.	(d)
5	RESET MIN/MAX	It resets the minimum / maximum values.	(d) (s)
6	SERIAL PRINT	It allows serial data to be transmitted, see the Serial value parameter on page 63.	(d)
7	TEACH PRESEL. 1	The current display value is stored as Preselection 1 (see the Preselection 1 parameter on page 50).	(d)
8	TEACH PRESEL. 2	The current display value is stored as Preselection 2 (see the Preselection 2 parameter on page 50).	(d)
9	TEACH PRESEL. 3	The current display value is stored as Preselection 3 (see the Preselection 3 parameter on page 50).	(d)
10	TEACH PRESEL. 4	The current display value is stored as Preselection 4 (see the Preselection 4 parameter on page 50).	(d)
11	SCROLL DISPLAY	It scrolls through the available display	(d)

		screens (see the "5.2 Screen structure during operation" section on page 27).	
12	CLEAR LOOP TIME	It clears all latched switching conditions.	
13	START PRESELECT	N.A.	
14	ACTIVATE DATA	N.A.	
15	STORE DATA	N.A.	
16	TESTPROGRAM	N.A.	
17	SET RED COLOR	The display lights up red. The colour can be changed by setting an event-dependent switching condition (see the parameters Event color 1 , Event color 2 , Event color 3 and Event color 4 in the "6.9 Preselection 1 menu" ... "6.12 Preselection 4 menu" on page 51 ff).	(d)
18	SET GREEN COLOR	The display lights up green. The colour can be changed by setting an event-dependent switching condition (see the parameters Event color 1 , Event color 2 , Event color 3 and Event color 4 in the "6.9 Preselection 1 menu" ... "6.12 Preselection 4 menu" on page 51 ff).	(d)
19	SET YELLOW COLOR	The display lights up yellow. The colour can be changed by setting an event-dependent switching condition (see the parameters Event color 1 , Event color 2 , Event color 3 and Event color 4 in the "6.9 Preselection 1 menu" ... "6.12 Preselection 4 menu" on page 51 ff).	(d)
20	INCREMENT BATCH	It increases the batch counter (see the Counter operation mode, "6.6 Counter operation mode menu" section on page 45).	(d)
21	DECREMENT BATCH	It decreases the batch counter (see the Counter operation mode, "6.6 Counter operation mode menu" section on page 45).	(d)
22	RESET/SET BATCH	It resets the batch counter (see the Counter operation mode, "6.6 Counter operation mode menu" section on page 45).	(d)

(s) = static switching (level evaluation)
Input 1 config. parameter must be set to be active at LOW / HIGH level
 (see options 0 – ACTIVE LOW and 1 – ACTIVE HIGH).

(d) = dynamic switching (edge evaluation)

Input 1 config. parameter must be set to activate at rising / falling edge (see options 2 – RISING EDGE and 3 – FALLING EDGE).

N.A. = not available

Input 1 config.

This parameter sets the switching characteristics of the input "10 - Ctrl. In 1".

0	ACTIVE LOW	It is active at "LOW" level (static)
1	ACTIVE HIGH	It is active at "HIGH" level (static)
2	RISING EDGE	It activates at rising edge
3	FALLING EDGE	It activates at falling edge

Input 2 action

This parameter sets the function of the input "11 - Ctrl. In 2". For complete information please refer to the **Input 1 action** parameter on page 66.

Input 2 config.

This parameter sets the switching characteristics of the input "11 - Ctrl. In 2". For complete information please refer to the **Input 1 config.** parameter on page 68.

Input 3 action

This parameter sets the function of the input "12 - Ctrl. In 3". For complete information please refer to the **Input 1 action** parameter on page 66.

Input 3 config.

This parameter sets the switching characteristics of the input "12 - Ctrl. In 3". For complete information please refer to the **Input 1 config.** parameter on page 68.

6.16 Display menu

The **Display** menu allows to set the features of the display.

Parameter changes become active only after exiting the menu selection.

Color

This parameter sets the colour of the display.

It is also possible to enable an event-dependent change of the colour of the display by setting a switching condition (see the parameters **Event color 1**, **Event color 2**, **Event color 3** and **Event color 4** in the "6.9 Preselection 1 menu" ... "6.12 Preselection 4 menu" on page 51 ff).

Event-dependent changes are only available for devices with order codes AVI, DO and RO.

0	RED	The display is coloured in red
1	GREEN	The display is coloured in green
2	YELLOW	The display is coloured in yellow

Brightness (%)

This parameter sets the brightness of the display in percent (%).

010	Min. brightness
090	Default value
100	Max. brightness

Contrast

This parameter sets the viewing angle.

0	Viewing angle from top
1	Viewing angle from centre
2	Viewing angle from bottom

Screen saver (s)

This parameter sets the time expressed in seconds before the display is switched off, starting from the last touch action.

A new touch action will activate the display again.

0000	Screen saver not active
...	
9999	Longest time before the screen saver is activated

Up-date time (s)

This parameter sets the update time of the display (refresh of the display), the value is expressed in seconds. It does not affect the parameter values.

0.005	Shortest update time
0.100	Default value
9.999	Longest update time

Font

This parameter sets the font style.

0	Standard
1	Font 1

6.17 Linearization menu

The linearisation function is configured in this menu. The linearisation points are available only when the **Speed**, **Process Time** or **Counter** operation modes are enabled (see on pages 37, 40 and 45 respectively). Furthermore this menu is displayed only if the **Linearization mode** parameter in the **General** menu (see on page 35) is set to either "1 – 1 QUADRANT" or "2 – 4 QUADRANT"; if 0 – OFF option is set the **Linearization** menu does not appear.

For a complete description of the linearisation function and some examples refer to the "6.17.1 Description of the linearisation function" section below.

P1(X)

...

P24(X)

X-coordinate of the linearisation point.

This value represents the display value the unit shows on the display without linearisation.

-99999999	Smallest X-coordinate
+0000000.0	Default value
+99999999	Largest X-coordinate

P1(Y)

...

P24(Y)

Y-coordinate of the linearisation point.

This is the display value the unit will show on the display after linearisation.



EXAMPLE

P2(X) parameter value will be replaced by **P2(Y)** parameter value.

-99999999	Smallest Y-coordinate
+0000000.0	Default value
+99999999	Largest Y-coordinate

6.17.1 Description of the linearisation function

The linearisation function allows to convert a linear input signal into a non-linear representation (or vice versa). 24 programmable X / Y coordinates (interpolation points) are available, they can be freely arranged over the whole conversion range at any desired distance. The unit uses linear interpolation between two coordinates. Therefore it is advisable to set several coordinates


where the curvature is greater and only few coordinates where the curvature is lesser.

If you need to set an individual linearisation curve, the **Linearization mode** parameter in the **General** menu (see on page 35) must be set to either "1 - 1 QUADRANT" or "2 - 4 QUADRANT" (see the diagrams below).

The parameters **P1(X)** to **P24(X)** are used to specify the coordinates on the x-axis. These are the measuring values that the unit would normally generate according to the actual input signal.

Parameters **P1(Y)** to **P24(Y)** are the values that the unit will generate instead of the X values, i.e. for instance **P5(Y)** replaces **P5(X)** etc.

The X coordinates must use continuously increasing settings, i.e. **P1(X)** must have the lowest setting while **P24(X)** must have the highest setting (**P1(X) < P2(X) < P3(X) ... < P23(X) < P24(X)**). If the measured value is greater than the last defined X value, the corresponding Y value is displayed.




If the **Linearization mode** parameter in the **General** menu is set to "1 - 1 QUADRANT", **P1(X)** parameter must be set to zero. Linearisation is only defined in the positive range and the negative range will be mirrored symmetrical with respect to the central point.

If the **Linearization mode** parameter in the **General** menu is set to "2 - 4 QUADRANT", **P1(X)** parameter can be set also to a negative value. If the measured value is smaller than **P1(X)**, **P1(Y)** is displayed.




EXAMPLE

The picture below shows a sluiceway where the gate is controlled by means of an incremental encoder. We want to display the opening of the gate "d", the existing encoder information is proportional to the angular information φ .



In this case we need to convert a non-linear input signal (incremental encoder signals φ) into a linear representation (opening of the gate "d"). In the x-axis we must set the actual values detected by the encoder while in the y-axis we will set the opening values of the gate.



7 - Appendix

7.1 Data readout via serial interface

All codes shown in the **Serial value** parameter (see the "6.13 Serial menu" section on page 61) are available for serial readout by a PC or a PLC. For communication the monitors use the Drivecom Protocol according to ISO 1745. All protocol details can be found in the user's guide "MAN Serial Protocol IFxx_LD25x_LD30x I_E.pdf". It is available for download from our web page www.lika.biz.

To request for a data transmission you must send the following request string to the converter:

EOT	AD1	AD2	C1	C2	ENQ
-----	-----	-----	----	----	-----

EOT = control character CTRL D (Hex 04)

AD1 = unit address, High Byte

AD2 = unit address, Low Byte

C1 = register code, High Byte

C2 = register code, Low Byte

ENQ = control character CTRL E (Hex 05)



EXAMPLE

The following example shows the request string for readout of the serial code = 1 from a unit having address "11":

ASCII code:	EOT	1	1	:	1	ENQ
Hex code:	04	31	31	3A	31	05
Binary code:	0000 0100	0011 0001	0011 0001	0011 1010	0011 0001	0000 0101

Following a correct request, the unit will respond:

STX	C1	C2	xxxxx	ETX	BCC
-----	----	----	-------	-----	-----

STX = control character CTRL B (Hex 02)

C1 = register code, High Byte

C2 = register code, Low Byte

xxxxx = readout data

ETX = control character CTRL C (Hex 03)

BCC = block check character

8 - Parameters / serial codes

8.1 General menu

See the "6.2 General menu" section on page 33

Parameter	Serial code	Value	Min. value	Max. value	Default value	Positions	Characters
Operational mode	0	3	0	4	0	1	0
Encoder properties LD350 Encoder properties LD355	1	0	0	3	0	1	0
Encoder supply	2	0	0	1	0	1	0
Counting direction	3	0	0	1	0	1	0
Scale units	4	29	0	29	0	2	0
Linearization mode	5	0	0	2	0	1	0
Pin preselection	6	0	0000	9999	0000	4	0
Pin parameter	7	0	0000	9999	0000	4	0
Back up memoryY	8	1	0	1	1	1	0
Factory settings	9	0	0	1	0	1	0
-	10	0	0	0	0	0	0
-	11	0	0	0	0	0	0

8.2 Speed operation mode menu

See the "6.3 Speed operation mode menu" section on page 37

Parameter	Serial code	Value	Min. value	Max. value	Default value	Positions	Characters
Display value	12	1000	00000001	99999999	100.0	8	0
Base frequency (Hz)	13	100	000001	500000	100	6	0
Decimal point	14	1	0	7	1	1	0
Sampling time (s)	15	100	0.005	9.999	0.100	4	3
Wait time (s)	16	100	0.01	99.99	01.00	4	2
Standstill time (s)	17	0	00.00	99.99	00.00	4	2
Average filter	18	0	0	8	0	1	0
For/Rev detection	19	0	0	1	0	1	0
-	20	0	0	0	0	0	0

8.3 Process Time operation mode menu

See the "6.4 Process Time operation mode menu" section on page 40

Parameter	Serial code	Value	Min. value	Max. value	Default value	Positions	Characters
Display format	21	0	0	4	0	1	0
Display value	22	1000	00000001	99999999	1000	8	0
Base frequency (Hz)	23	100	000001	500000	100	6	0
Sampling time (s)	24	100	0.005	9.999	0.100	4	3
Wait time (s)	25	100	00.01	99.99	01.00	4	2
Standstill time (s)	26	0	00.00	99.99	00.00	4	2
Average filter	27	0	0	8	0	1	0
-	28	0	0	0	0	0	0
-	29	0	0	0	0	0	0

8.4 Timer operation mode menu

See the "6.5 Timer operation mode menu" section on page 43

Parameter	Serial code	Value	Min. value	Max. value	Default value	Positions	Characters
Time base	30	7	0	7	0	1	0
Start / Stop	31	2	0	3	2	1	0
Auto set / reset	32	0	0	1	0	1	0
Latch function	33	0	0	1	0	1	0
Set value	34	0	00000.000	99999999	0	8	0
Inc / Dec mode	35	0	0	1	0	1	0

8.5 Counter operation mode menu

See the "6.6 Counter operation mode menu" section on page 45

Parameter	Serial code	Value	Min. value	Max. value	Default value	Positions	Characters
Count mode	36	3	0	5	3	1	0
Factor	37	1000	00.00001	99.99999	1.00000	7	5
Set value	38	0	-99999999	99999999	+0	+/- 8	0
Decimal point	39	0	0	7	0	1	0
Batch mode	40	1	0	3	0	1	0
Batch set value	41	0	00000000	99999999	0	8	0
-	42	0	0	0	0	1	0

8.6 Velocity operation mode menu

See the "6.7 Velocity operation mode menu" section on page 48

Parameter	Serial code	Value	Min. value	Max. value	Default value	Positions	Characters
Start / Stop	A0	0	0	3	0	1	0
Display value	A1	1000	00000001	99999999	1000	8	0
Base time (s)	A2	1000	000.001	999.999	1.000	6	3
Decimal point	A3	0	0	7	0	1	0
Wait time (s)	A4	0	00.00	99.99	0	4	2
Standstill time (s)	A5	0	00.00	99.99	0	4	2
-	A6	0	0	0	0	0	0
-	A7	0	0	0	0	0	0

8.7 Preselection values menu

See the "6.8 Preselection values menu" section on page 50

Parameter	Serial code	Value	Min. value	Max. value	Default value	Positions	Characters
Preselection 1	A8	1000	-9999999.9	9999999.9	100.0	+/- 8	0
Preselection 2	A9	2000	-9999999.9	9999999.9	200.0	+/- 8	0
Preselection 3	B0	3000	-9999999.9	9999999.9	300.0	+/- 8	0
Preselection 4	B1	4000	-9999999.9	9999999.9	400.0	+/- 8	0

8.8 Preselection 1 menu

See the "6.9 Preselection 1 menu" section on page 51

Parameter	Serial code	Value	Min. value	Max. value	Default value	Positions	Characters
Mode 1	B2	7	0	9	0	1	0
Hysteresis 1	B3	0	000.0	99999	0	5	0
Pulse time 1 (s)	B4	500	00.000	60.000	0	5	3
Output target 1	B5	1	0	6	1	1	0
Output polarity 1	B6	0	0	1	0	1	0
Output lock 1	B7	0	0	1	0	1	0
Start up delay 1 (s)	B8	0	00.000	60.000	0	5	3
Event color 1	B9	0	0	3	0	1	0

8.9 Preselection 2 menu

See the "6.10 Preselection 2 menu" section on page 55

Parameter	Serial code	Value	Min. value	Max. value	Default value	Positions	Characters
Mode 2	C0	0	0	9	0	1	0
Hysteresis 2	C1	0	000.0	99999	0	5	0
Pulse time 2 (s)	C2	0	00.000	60.000	0	5	3
Output target 2	C3	2	0	6	1	1	0
Output polarity 2	C4	0	0	1	0	1	0
Output lock 2	C5	0	0	1	0	1	0
Start up delay 2 (s)	C6	0	00.000	60.000	0	5	3
Event color 2	C7	0	0	3	0	1	0

8.10 Preselection 3 menu

See the "6.11 Preselection 3 menu" section on page 57

Parameter	Serial code	Value	Min. value	Max. value	Default value	Positions	Characters
Mode 3	C8	0	0	9	0	1	0
Hysteresis 3	C9	0	000.0	99999	0	5	0
Pulse time 3 (s)	D0	0	00.000	60.000	0	5	3
Output target 3	D1	3	0	6	1	1	0
Output polarity 3	D2	0	0	1	0	1	0
Output lock 3	D3	0	0	1	0	1	0
Start up delay 3 (s)	D4	0	0	1	0	1	0
Event color 3	D5	0	0	3	0	1	0

8.11 Preselection 4 menu

See the "6.12 Preselection 4 menu" section on page 59

Parameter	Serial code	Value	Min. value	Max. value	Default value	Positions	Characters
Mode 4	D6	0	0	9	0	1	0
Hysteresis 4	D7	0	000.0	99999	0	5	0
Pulse time 4 (s)	D8	0	00.000	60.000	0	5	3
Output target 4	D9	4	0	6	1	1	0
Output polarity 4	E0	0	0	1	0	1	0
Output lock 4	E1	0	0	1	0	1	0
Start up delay 4 (s)	E2	0	0	1	0	1	0
Event color 4	E3	0	0	3	0	1	0

8.12 Serial menu

See the "6.13 Serial menu" section on page 61

Parameter	Serial code	Value	Min. value	Max. value	Default value	Positions	Characters
Unit number	90	11	11	99	11	2	0
Serial baud rate	91	0	0	2	0	1	0
Serial format	92	0	0	9	0	1	0
Serial init	9~	0	0	1	0	1	0
Serial protocol	E4	0	0	1	0	1	0
Serial timer (s)	E5	0	00.000	60.000	0	5	3
Serial value	E6	0	0	9	0	1	0
-	E7	0	0	0	0	0	0

8.13 Analog menu

See the "6.14 Analog menu" section on page 64

Parameter	Serial code	Value	Min. value	Max. value	Default value	Positions	Characters
Analog format	E8	0	0	2	0	1	0
Analog start	E9	0	-99999999	99999999	0.0	+/- 8	0
Analog end	F0	10000	-99999999	99999999	1000.0	+/- 8	0
Analog gain (%)	F1	10000	000.00	110.00	100.00	5	2
Analog offset	F2	0	-99.99	99.99	0.00	84	2
-	F3	0	0	0	0	0	0
-	F4	0	0	0	0	0	0

8.14 Command menu

See the "6.15 Command menu" section on page 66

Parameter	Serial code	Value	Min. value	Max. value	Default value	Positions	Characters
Input 1 action	F5	20	0	22	0	2	0
Input 1 config.	F6	2	0	3	2	1	0
Input 2 action	F7	21	0	22	0	2	0
Input 2 config.	F8	2	0	3	2	1	0
Input 3 action	F9	22	0	22	0	2	0
Input 3 config.	G0	2	0	3	2	1	0
-	G1	0	0	0	0	1	0
-	G2	0	0	0	0	1	0
-	G3	0	0	0	0	1	0
-	G4	0	0	0	0	1	0
-	G5	0	0	0	0	1	0

8.15 Display menu

See the "6.16 Display menu" section on page 69

Parameter	Serial code	Value	Min. value	Max. value	Default value	Positions	Characters
Color	G6	0	0	2	0	1	0
Brightness (%)	G7	90	010	100	090	3	0
Contrast	G8	1	0	2	1	1	0
Screen saver (s)	G9	0	0000	9999	0	4	0
Up-date time (s)	H0	100	0.005	9.999	0.100	4	3
Font	H1	0	0	1	0	1	0
-	H2	0	0	0	0	1	0
-	H3	0	0	0	0	1	0
-	H4	0	0	0	0	1	0

8.16 Linearization menu

See the "6.17 Linearization menu" section on page 71

Parameter	Serial code	Value	Min. value	Max. value	Default value	Positions	Characters
P1(X)	H5	0	-99999999	99999999	0.0	+/- 8	0
P1(Y)	H6	0	-99999999	99999999	0.0	+/- 8	0
P2(X)	H7	0	-99999999	99999999	0.0	+/- 8	0
P2(Y)	H8	0	-99999999	99999999	0.0	+/- 8	0
P3(X)	H9	0	-99999999	99999999	0.0	+/- 8	0
P3(Y)	I0	0	-99999999	99999999	0.0	+/- 8	0
P4(X)	I1	0	-99999999	99999999	0.0	+/- 8	0
P4(Y)	I2	0	-99999999	99999999	0.0	+/- 8	0
P5(X)	I3	0	-99999999	99999999	0.0	+/- 8	0
P5(Y)	I4	0	-99999999	99999999	0.0	+/- 8	0
P6(X)	I5	0	-99999999	99999999	0.0	+/- 8	0
P6(Y)	I6	0	-99999999	99999999	0.0	+/- 8	0
P7(X)	I7	0	-99999999	99999999	0.0	+/- 8	0
P7(Y)	I8	0	-99999999	99999999	0.0	+/- 8	0
P8(X)	I9	0	-99999999	99999999	0.0	+/- 8	0
P8(Y)	J0	0	-99999999	99999999	0.0	+/- 8	0
P9(X)	J1	0	-99999999	99999999	0.0	+/- 8	0
P9(Y)	J2	0	-99999999	99999999	0.0	+/- 8	0
P10(X)	J3	0	-99999999	99999999	0.0	+/- 8	0
P10(Y)	J4	0	-99999999	99999999	0.0	+/- 8	0
P11(X)	J5	0	-99999999	99999999	0.0	+/- 8	0
P11(Y)	J6	0	-99999999	99999999	0.0	+/- 8	0

(continue on next page)

(continued)

Parameter	Serial code	Value	Min. value	Max. value	Default value	Positions	Characters
P12(X)	J7	0	-99999999	99999999	0.0	+/- 8	0
P12(Y)	J8	0	-99999999	99999999	0.0	+/- 8	0
P13(X)	J9	0	-99999999	99999999	0.0	+/- 8	0
P13(Y)	K0	0	-99999999	99999999	0.0	+/- 8	0
P14(X)	K1	0	-99999999	99999999	0.0	+/- 8	0
P14(Y)	K2	0	-99999999	99999999	0.0	+/- 8	0
P15(X)	K3	0	-99999999	99999999	0.0	+/- 8	0
P15(Y)	K4	0	-99999999	99999999	0.0	+/- 8	0
P16(X)	K5	0	-99999999	99999999	0.0	+/- 8	0
P16(Y)	K6	0	-99999999	99999999	0.0	+/- 8	0
P17(X)	K7	0	-99999999	99999999	0.0	+/- 8	0
P17(Y)	K8	0	-99999999	99999999	0.0	+/- 8	0
P18(X)	K9	0	-99999999	99999999	0.0	+/- 8	0
P18(Y)	L0	0	-99999999	99999999	0.0	+/- 8	0
P19(X)	L1	0	-99999999	99999999	0.0	+/- 8	0
P19(Y)	L2	0	-99999999	99999999	0.0	+/- 8	0
P20(X)	L3	0	-99999999	99999999	0.0	+/- 8	0
P20(Y)	L4	0	-99999999	99999999	0.0	+/- 8	0
P21(X)	L5	0	-99999999	99999999	0.0	+/- 8	0
P21(Y)	L6	0	-99999999	99999999	0.0	+/- 8	0
P22(X)	L7	0	-99999999	99999999	0.0	+/- 8	0
P22(Y)	L8	0	-99999999	99999999	0.0	+/- 8	0
P23(X)	L9	0	-99999999	99999999	0.0	+/- 8	0
P23(Y)	M0	0	-99999999	99999999	0.0	+/- 8	0
P24(X)	M1	0	-99999999	99999999	0.0	+/- 8	0
P24(Y)	M2	0	-99999999	99999999	0.0	+/- 8	0

8.17 Serial codes of commands

Serial code	Command
54	RESET/SET
55	FREEZE DISPLAY
56	TOUCH DISABLE
57	CLR LOCK
58	CLR MIN MAX
59	SERIAL PRINT
60	TEACH PRES 1
61	TEACH PRES 2
62	TEACH PRES 3
63	TEACH PRES 4
64	SCROLL_DISPLAY
65	CLEAR LOOP TIME
66	START PRESELECTION
67	ACTIVATE DATA
68	STORE EEPROM
69	TESTPROGRAM

This page intentionally left blank

Document release	Release date	Description
1.0	27.09.2018	First issue



Dispose separately

lika

Lika Electronic

Via S. Lorenzo, 25 • 36010 Carrè (VI) • Italy

Tel. +39 0445 806600

Fax +39 0445 806699



info@lika.biz • www.lika.biz